



ENGLISH



KT610 | USER GUIDE |

| KT610 | USER GUIDE

LG Electronics Inc.
<http://www.lgmobile.com>

P/N : MMBB0306604 (1.0) H

CE 0168

| KT610 | USER GUIDE

LG Electronics Inc.

Bluetooth QD ID B012388

ENGLISH

| KT610 | USER GUIDE

Please read this manual carefully
before operating your mobile phone.
Retain it for future reference.



Table of Contents

Introduction	4	Profiles	38
For Your Safety	5	Browser	39
Guidelines for safe and efficient use	6	Browsing the web	
KT610 Features	12	Saved pages	
Parts of the phone		Auto. Bookmarks	40
Getting started	16	Browser feeds	
General functions	21	Log	41
Menu tree	31	Recent calls	
Google	32	Call duration	
Search		Packet data	
Maps		Messaging	42
Mail		New message	
YouTube		Inbox	45
Multimedia	33	My folders	
RealPlayer		Mailbox	
Music player		Drafts	46
Recorder	34	Sent	
Camera	35	Outbox	
Flash Player	37	Reports	
		Contacts	47
		New contact	
		Contacts list	
		Groups	

Connectivity 48

Conn.mgr.	
Bluetooth	
USB	49
Sync	50

Organiser 51

Calendar	
Clock	
Notes	52
Quickoffice	
Calculator	53
Converter	
File mgr.	
Memory	54

My stuff 55

Images	
Video clips	56
Tracks	
Sound clips	
Streaming links	
Presentations	57
All files	

Tools 58

Installations	
Call mailbox	
Speed dial	
Themes	59
Actv. keys	60
App. mgr.	61
GPS data	62
Landmarks	63
Device mgr.	
Help	
About	

Settings 64

General	
Phone	65
Connection	67
Applications	70

Accessories 71**Technical data 72**

Introduction

Congratulations on your purchase of the advanced and compact KT610 3G video mobile phone, designed to operate with the latest digital mobile communication technology.



This user's guide contains important information on the use and operation of this phone. Please read all the information carefully for optimal performance and to prevent any damage to or misuse of the phone. Any changes or modifications not expressly approved in this user's guide could void your warranty for this equipment.

For Your Safety

Please read these simple guidelines. Not following these guidelines may be dangerous or illegal. Further detailed information is given in this manual.

Warning

- ▶ Mobile Phones must be switched off at all times in aircrafts.
- ▶ Do not hold the phone in your hand while driving.
- ▶ Do not use your phone near petrol stations, fuel depots, chemical plants or blasting operations.
- ▶ For your safety, use ONLY specified ORIGINAL batteries and chargers.
- ▶ Do not handle the phone with wet hands while it is being charged. It may cause an electric shock or seriously damage your phone.
- ▶ Keep the phone in a safe place out of small children's reach. It includes small parts which, if detached, may cause a choking hazard.

Caution

- ▶ Switch off the phone in any area where required by special regulations. For example, do not use your phone in hospitals or it may affect sensitive medical equipment.
- ▶ Emergency calls may not be available under all mobile networks. Therefore, you should never depend solely on your mobile phone for emergency calls.
- ▶ Only use ORIGINAL accessories to avoid damage to your phone.
- ▶ All radio transmitters carry risks of interference with electronics in close proximity. Minor interference may affect TVs, radios, PCs, etc.
- ▶ Batteries should be disposed of in accordance with relevant legislation.
- ▶ Do not dismantle the phone or battery.

Guidelines for safe and efficient use

Please read these simple guidelines. Not following these guidelines may be dangerous or illegal. Further detailed information is given in this manual.

Certification information (SAR)

THIS DEVICE MEETS INTERNATIONAL GUIDELINES FOR EXPOSURE TO RADIO WAVES

Your mobile device is a radio transmitter and receiver. It is designed and manufactured not to exceed the limits for exposure to radio frequency (RF) recommended by international guidelines (ICNIRP). These limits are part of comprehensive guidelines and establish permitted levels of RF energy for the general population. The guidelines were developed by independent scientific organisations through periodic and thorough evaluation of scientific studies. The guidelines include a substantial

safety margin designed to assure the safety of all persons, regardless of age and health.

The exposure standard for mobile devices employs a unit of measurement known as the Specific Absorption Rate, or SAR. The SAR limit stated in the international guidelines is 2.0 W/kg*. Tests for SAR are conducted using standard operating positions with the device transmitting at its highest certified power level in all tested frequency bands. Although the SAR is determined at the highest certified power level, the actual SAR of the device while operating can be well below the maximum value. This is because the device is designed to operate at multiple power levels so as to use only the power required to reach the network. In general, the closer you are to a base station, the lower the power output of the device. Before a phone model is available for sale to the public, compliance with the European

R&TTE directive must be shown. This directive includes as one essential requirement the protection of the health and the safety for the user and any other person. The highest SAR value for this device when tested for use at the ear is 0,537 W/kg.

This device meets RF exposure guidelines when used either in the normal use position against the ear or when positioned at least 1.5 cm away from the body. When a carry case, belt clip or holder is used for body-worn operation, it should not contain metal and should position the product at least 1.5 cm away from your body. In order to transmit data files or messages, this device requires a quality connection to the network. In some cases, transmission of data files or messages may be delayed until such a connection is available. Ensure the above separation distance instructions are followed until the transmission is completed. The highest SAR value for this device

when tested for use at the body is 1,32 W/kg.

* The SAR limit for mobile devices used by the public is 2.0 watts/kilogram (W/kg) averaged over ten grams of body tissue. The guidelines incorporate a substantial margin of safety to give additional protection for the public and to account for any variations in measurements. SAR values may vary depending on national reporting requirements and the network band. For SAR information in other regions please look under product information at www.lgmobile.com.

Guidelines for safe and efficient use

Product care and maintenance

WARNING! *Only use batteries, chargers and accessories approved for use with this particular phone model. The use of any other types may invalidate any approval or warranty applying to the phone, and may be dangerous.*

- ▶ Do not disassemble this unit. Take it to a qualified service technician when repair work is required.
- ▶ Keep away from electrical appliances such as a TV's, radios or personal computers.
- ▶ The unit should be kept away from heat sources such as radiators or cookers.
- ▶ Never place your phone in a microwave oven as it will cause the battery to explode.
- ▶ Do not drop.
- ▶ Do not subject this unit to mechanical vibration or shock.
- ▶ The coating of the phone may be damaged if covered with wrap or vinyl wrapper.
- ▶ Do not use harsh chemicals (such as alcohol, benzene, thinners, etc.) or detergents to clean your phone. There is a risk of this causing a fire.
- ▶ Do not subject this unit to excessive smoke or dust.
- ▶ Do not keep the phone next to credit cards or transport tickets; it can affect the information on the magnetic strips.
- ▶ Do not tap the screen with a sharp object as it may damage the phone.
- ▶ Do not expose the phone to liquid or moisture.
- ▶ Use accessories, such as earphones and headsets, with caution. Ensure that cables are tucked away safely and do not touch the antenna unnecessarily.
- ▶ Please remove the data cable before powering on the handset.

Efficient phone operation

To enjoy optimum performance with minimum power consumption please.

- ▶ Do not hold the antenna when the phone is in use. If you hold it, it can affect call quality, it may also cause the phone to operate at a higher power level than needed and shorten talk and standby times.

Electronic devices

All mobile phones may get interference, which could affect performance.

- ▶ Do not use your mobile phone near medical equipment without requesting permission. Avoid placing the phone over pacemakers (i.e. in your breast pocket.)
- ▶ Some hearing aids might be disturbed by mobile phones.

- ▶ Minor interference may affect TVs, radios, PCs, etc.

Road safety

Check the laws and regulations on the use of mobile phones in the areas when you drive.

- ▶ Do not use a hand-held phone while driving.
- ▶ Give full attention to driving.
- ▶ Use a hands-free kit, if available.
- ▶ Pull off the road and park before making or answering a call if driving conditions so require.
- ▶ RF energy may affect some electronic systems in your motor vehicle such as a car stereo or safety equipment.
- ▶ If your vehicle is equipped with an air bag, do not obstruct it with installed or portable wireless equipment. It can cause serious injury due to improper performance.

Guidelines for safe and efficient use

If you are listening to music whilst outside and about, please ensure that the volume is at a reasonable level so that you are aware of your surroundings. This is particularly imperative when attempting to cross the street.

Avoid damage to your hearing

Damage to your hearing can occur if you are exposed to loud sound for long periods of time. We therefore recommend that you do not turn on or off the handset close to your ear. We also recommend that music and call volumes are set to a reasonable level.

Blasting area

Do not use the phone where blasting is in progress. Observe restrictions, and follow any regulations or rules.

Potentially explosive atmospheres

- ▶ Do not use the phone at a refueling point. Don't use near fuel or chemicals.
- ▶ Do not transport or store flammable gas, liquid, or explosives in the compartment of your vehicle, which contains your mobile phone and accessories.

In aircraft

Wireless devices can cause interference in aircraft.

- ▶ Turn off your mobile phone before boarding any aircraft.
- ▶ Do not use it on the ground without crew permission.

Children

Keep the phone in a safe place out of small children's reach. It includes small parts which if detached may cause a choking hazard.

Emergency calls

Emergency calls may not be available under all mobile networks. Therefore, you should never depend solely on your mobile phone for emergency calls. Check with your local service provider.

Battery information and care


- ▶ You do not need to completely discharge the battery before recharging. Unlike other battery systems, there is no memory effect that could compromise the battery's performance.
- ▶ Use only LG batteries and chargers. LG chargers are designed to maximize the battery life.
- ▶ Do not disassemble or short-circuit the battery pack.
- ▶ Keep the metal contacts of the battery pack clean.
- ▶ Replace the battery when it no longer provides acceptable performance. The battery pack may be recharged hundreds of times until it needs replacing.
- ▶ Recharge the battery if it has not been used for a long time to maximize usability.
- ▶ Do not expose the battery charger to direct sunlight or use it in high humidity, such as the bathroom.
- ▶ Do not leave the battery in hot or cold places, this may deteriorate the battery performance.
- ▶ Risk of explosion if battery is replaced by an incorrect type.
- ▶ Dispose of used batteries according to the manufacturer's instructions.
- ▶ If you need to replace the battery, take it to the nearest authorized LG Electronics service point or dealer for assistance.
- ▶ Always unplug the charger from the wall socket after the phone is fully charged to save unnecessary power consumption of the charger.

KT610 Features

Parts of the phone

Open view





KT610 Features

KT610 Features

Left side view



Side keys

Note

- To protect your hearing, maximum volume level is 10.

Right side view



Micro SD memory card slot




Headset/Charger/Cable connector

Note

- Please ensure phone is powered on and in standby mode before connecting the USB cable.

Rear view



Getting started

Installing the SIM card and battery

1. Installing the SIM card.

Your SIM card contains your phone number, service details and contacts and must be inserted into your handset. Always disconnect the charger and other accessories from your handset before inserting and removing your SIM card. Slide the SIM card into the SIM card holder. Make sure that the SIM card is properly inserted and the gold contact area on the card is facing downwards. To remove the SIM card, press down lightly and pull it in the reverse direction.



To insert the SIM card


To remove the SIM card

Note

► The metal contact of the SIM card can easily be damaged by scratches. Pay special attention to the SIM card while handling. Follow the instructions supplied with the SIM card.

2. Install the battery.


Slide the battery upwards until it snaps back into place.



3. To remove the battery.

Turn the power off. (If the power is left on, there is a chance you could lose the stored telephone numbers and messages.)

Press and hold down the battery release button and slide the battery down.




Charging the battery

Before connecting the travel adapter to the phone you must first install the battery.



1. With the arrow facing you as shown in the diagram push the plug on the battery adapter into the socket on the left side of the phone until it clicks into place.
2. Connect the other end of the travel adapter to the mains socket.



Note

► Only use the charger included in the box.

3. The moving bars on the battery icon will stop after charging is complete.
4. Ensure the battery is fully charged before using the phone for the first time.

Getting started

Caution

- ▶ Do not force the connector as this may damage the phone and/or the travel adapter.
- ▶ If you use the battery pack charger when abroad, use an attachment plug adaptor for the proper configuration.
- ▶ Do not remove your battery or the SIM card while charging.

Warning

- ▶ Unplug the power cord and charger during lightning storms to avoid electric shock or fire.
- ▶ Make sure that no sharp-edged items such as animal teeth or nails, come into contact with the battery. This may cause a fire.

Disconnecting the charger

Disconnect the charger from the phone as shown in the diagram below.



How to use a memory card



<Memory card>

<How to insert memory card>

- 1 Turn the phone off. Inserting or removing the memory card when the phone is on may damage the files stored in the memory card.
- 2 Lift the plastic cover which protects the slot.



- 3 Insert the memory card into the slot. The gold contacts behind memory card must be facing down while inserting into the

phone. Don't push the memory card too much. If it doesn't go into the slot easily, you may be trying to insert it in the wrong way or there could be a foreign object in the slot.

- 4 Once inserted, push the memory card until you hear a 'Click', meaning that the memory card has been correctly engaged.



- 5 Close the plastic slot protection.
- 6 To remove the memory card, open the slot protection and push the memory card to unlock it. Carefully extract the memory card.

Attention:

- ▶ Avoid using the memory card when the battery is low.
- ▶ When writing to the card, wait for the operation to complete before removing the card.
- ▶ The card is designed to fit easily into the system one way only.
- ▶ Do not bend the card or force it into the slot.
- ▶ Do not insert any memory cards other than those made by memory card.
- ▶ If the memory card has been formatted using FAT32, format the memory card using FAT16 again.

For more information on the memory card, please refer to the memory card instruction manual.

Getting started

Memory card formatting

Before you start to use the memory card you have to format it. After you insert the memory card, select  → **Organiser** → **Memory**, then press .

This operation should only be done when you insert the memory card for the first time. During formatting various folders will be created for different data types.

Turning the handset on/off

Turning your handset on

Ensure that your SIM card is in your handset and the battery is charged. Press and hold  until the power comes on. Enter the SIM PIN code that was supplied with your SIM card if the PIN code request is set to On. After a few seconds you will be registered on the network.

Turning your handset off

Press and hold  until the power goes off. Or press  and select Switch off!. There may be a few seconds delay while the handset powers down. Do not turn the handset on again during this time.

General functions

Making and answering calls

Making a voice call

1. Enter the number including the full area code.

- ▶ To delete a digit press  .
To delete all digits press and hold  .

2. Press  to make the call.

3. When you have a call in progress, you can access the followings by pressing the left soft key [Options].

- ▶ **Activate loudspeaker/handset:** You can switch on/off the loudspeaker to allow others nearby to participate in the conversation, for example.
- ▶ **End active call:** Select this if you want to finish active call.
- ▶ **Hold:** Select this to put a caller on hold. Select **Unhold** to continue your conversation.

- ▶ **Call Mute:** Select this to switch the microphone off. To switch it back on, press Unmute.

- ▶ **New call:** Select this to make a new call. Activating call is automatically held.

- ▶ **Open active standby:** select this to open active standby screen.

- ▶ **Conference:** Select this to create a conference call to converse with multiple people at the same time.

Tip

- ▶ *To add a participant to a conference call, call the new participant, press the left soft key [Options] and select Conference > Add to conference.*

- ▶ **Switch to video call:** Ends the active call and automatically make a video call to the same number.

- ▶ **Send MMS:** You can send a media file to the other party as a multimedia message.

General functions

- **Send DTMF:** To send touch tones.

Tip

- *While a call is in progress, you can press the number keys to send DTMF tones. You can use DTMF tones to communicate with voice mailboxes and computerised telephony systems.*

- **Help:** Use this option to get to know the phone feature.

4. Press  to finish the call, or close the handset.

Making a call from the call logs

1. In standby mode, press  and the latest incoming, outgoing and missed phone numbers will be displayed.
2. Select the desired number by using the up/down navigation keys.
3. Press  to call the number.

Making a Video call

You can make a video call in a 3G covered service area. If the called user has a 3G video phone in a 3G covered service area, the call will be established. You can also answer a video call for video incoming call.

1. Input the phone number using the keypad, or select the phone number from the calls made/received lists.

- To correct mistakes, press  briefly to delete the last number, or press and hold  to delete all numbers.

2. If you do not want to use the speakerphone, ensure you have the headset plugged in.

3. To start the video function, press the left soft key [Options] and select **Call → Video call**.

- You will be notified that you will need to close other applications to make the video call.

Note

- ▶ *The video call may take some time to connect.*

4. Adjust the camera position if necessary.
5. When you have a video call in progress, you can access the followings by pressing the left soft key [Options].

▶ **Enable**

- Sending video: Select this to send your own video image.
- Sending audio: Select this to unmute the microphone so as to allow audio sending.
- Sending aud. & video: Select this to send your video and audio.

Note

- ▶ *You can zoom your video image in or out using up /down navigation keys.*

▶ **Disable**

- Sending video: Select this not to send your video image.

- Sending audio: Select this to mute the microphone so as not to allow audio sending.

- Sending aud. & video: Select this not to send your video and audio.

- ▶ **Activate loudspeaker/handset:** You can switch on/off the loudspeaker to allow others nearby to participate in the conversation, for example.

- ▶ **Video preference:** Select **Clearer detail** to set received video quality preference with a lower frame rate but a good image quality. Select **Smoother video** to use a higher frame rate but a lower image quality.

- ▶ **Send snapshot:** You can take a picture and send it to the other party. Press **Capture** to take the picture and **Use video** to return to the regular video call after sending it.

General functions

- ▶ **Share image:** You can send an image in the **Image** folder in **My stuff**.
- ▶ **End active call:** Select this to answer a video call while you already have another video or voice call in progress.
- ▶ **Open active standby:** To open the standby mode image on the display.
- ▶ **Use secondary camera:** Select this to use the secondary camera.
- ▶ **Change image order:** To switch the location of the other party's and your own video or still image on the display.
- ▶ **Zoom in/out:** You can zoom your video image in or out.
- ▶ **Switch to voice call:** Ends the video call and automatically redial the same number for a regular voice call.

- ▶ **Help:** Use this option to get to know the phone feature.

6. Press  to finish the call, or close the handset.

Making a voice/video call from Contacts

It is easy to call anyone whose number you have stored in your Contacts.

1. Move the joystick to the down to access the contacts list.
2. Scroll to the contact to make a call.
3. Press  to make a voice call. Press the left soft key and select **Make video call** to make a video call.
4. Press  to finish the call.

Making international calls

1. Press  twice for the international prefix. The '+' character prefixes the international access code.
2. Enter the country code, area code, and the phone number.

3. Press  .

Adjusting the volume

During a call, if you want to adjust the earpiece volume, use () on the left side of the phone.

Answering a call

When you receive a call, the phone rings and the flashing phone icon appears on the screen. If the caller can be identified, the caller's phone number (or name if stored in your Contacts) is displayed.

1. Press  to answer an incoming call.

Note

- ▶ To reject an incoming call, press  or the right soft key twice.
- ▶ If Anykey answer is set to On (Menu → Settings → Phone → Call → Anykey answer), any key will answer a call except .

2. End the call by pressing .

Note

- ▶ You can answer a call while using the Contacts or other menu features.
- ▶ When the compatible headset is connected, you can also answer a call using the headset key, as well as using the phone. To reject an incoming call, press .
- ▶ You can mute the ringtone when a call comes in by pressing the right soft key [Silence].

Shortcut to activate silent mode

You can activate the silent mode by pressing and holding down  when Flip of the phone is closed. Or press  and select **Silent**.

Entering text

You can enter alphanumeric characters using the keypad.

For example, storing names in Contacts, writing a message, creating a personal greeting or scheduling events in the calendar all require

General functions

entering text. The following text input methods are available with the handset.

T9 Mode

 Abc  abc

This mode lets you enter words with only one keystroke per letter. Each key on the keypad has more than one letter. The T9 mode automatically compares your keystrokes with an internal dictionary to determine the correct word, thus requiring far fewer keystrokes than the traditional ABC mode. This is sometimes known as predictive text.

Mode  Abc  abc

This mode lets you enter letters by pressing the key labeled with the required letter once, twice, three or four times until the letter is displayed.

123 Mode (Numbers Mode)

 123

Type numbers using one keystroke per number. To change to 123 mode in a text entry field, press the  key until 123 mode is displayed.

Changing the text input mode

When you are in a field that allows characters to be entered, you will notice the text input mode indicator in the upper right corner of the LCD screen.

► Press  to cycle between  Abc,  abc,  Abc,  abc.

► Press and hold  to switch between text entry mode and number entry mode.

Using the T9 Mode

The T9 predictive text input mode allows you to enter words easily with a minimum number of key presses.

As you press each key, the handset begins to display the characters that it thinks you are typing based on a built-in dictionary. As new letters are added, the word changes to reflect the most likely candidate from the dictionary.

1. When you are in the T9 predictive text input mode, start entering a word by pressing **2_{abc}** to **9_{wnyz}**. Press one key per letter.

- ▶ The word changes as letters are typed. Ignore what's on the screen until the word is typed completely.
- ▶ If the word is still incorrect after typing completely, press ***+** once or more to scroll through the other word options.

Example

Press **2_{abc}** **4_{ghi}** **2_{abc}** **6_{mno}** to type **Good**.

Press ***+** to get **Home**.

- ▶ If the desired word is missing from the word choices list, add it by using the ABC mode.

2. Enter the whole word before editing or deleting any keystrokes.
3. Complete each word with a space by pressing **0_␣**.

To delete letters, press **↶**. You can press and hold down **↶** until the entire words are deleted.

Using the ABC Mode

Use **2_{abc}** to **9_{wnyz}** to enter your text.

1. Press the key labelled with the required letter:
 - ▶ Once for the first letter.
 - ▶ Twice for the second letter.
 - ▶ And so on.
2. To insert a space, press **0_␣** once. To delete letters, press **↶**. Press and hold down **↶** to clear the display.

General functions

Using the 123 (Number) mode

The 123 mode enables you to enter numbers in a message(a telephone number, for example). Press the keys corresponding to the required digits before manually switching back to the appropriate text entry mode.

In the text entry mode, you can enter numbers by long press on the corresponding keys.

Using the symbol mode

The symbol mode enables you to enter various symbols or special characters.

1. To enter a symbol, press Edit key [] and select **More symbols**.
The symbol list window is shown up.
2. After selecting the desired one using navigation keys, press .

On-screen icons

Icon	Description
	The device is being used in a GSM network.
3G	The device is being used in a UMTS network (network service).
	You have one or more unread messages in the Inbox folder in Messag.
	There are messages waiting to be sent in the Outbox folder.
	You have missed calls.
	Shown if Ringing type is set to Silent and Message alert tone, IM alert tone, and E-mail alert tone are set to Off.
	The device keypad is locked.
	A clock alarm is active.
2	The second phone line is being used (network service).
	All calls to the device are diverted to another number. If you have two phone lines(network service), the indicator for the first line is  and for the second  .
	GPS application is in use.
	A compatible headset is connected to the device.
	A GPRS packet data connection is available.
	A GPRS packet data connection is active.
	A GPRS packet data connection is on hold.

General functions

Icon	Description
	A EDGE packet data connection is available.
	A EDGE packet data connection is active.
	A EDGE packet data connection is on hold.
	A UMTS packet data connection is available.
	A UMTS packet data connection is active.
	A UMTS packet data connection is on hold.
	A HSDPA packet data connection is available.
	A HSDPA packet data connection is active.
	A HSDPA packet data connection is on hold.
	Bluetooth connectivity is on.
	Data is being transmitted using Bluetooth connectivity.
	A USB connection is active.

Menu tree

Menu tree

1. Google		0. My stuff
1.1 Search	6.1 New message	Images
1.2 Maps	6.2 Inbox	Video clips
1.3 Mail	6.3 My folders	Tracks
1.4 YouTube	6.4 Mailbox	Sound clips
	6.5 Drafts	Streaming links
2. Multimedia	6.6 Sent	Presentations
2.1 RealPlayer	6.7 Outbox	All files
2.2 Music player	6.8 Reports	
2.3 Recorder		*. Tools
2.4 Camera	7. Contacts	*.1 Installations
2.5 Flash Player		*.2 Call mailbox
	8. Connectivity	*.3 Speed dial
3. Profiles	8.1 IM	*.4 Themes
3.1 General	8.2 Conn. Mgr.	*.5 Actv. keys
3.2 Silent	8.3 Bluetooth	*.6 App. mgr.
3.3 Meeting	8.4 USB	*.7 GPS data
3.4 Outdoor	8.5 Sync	*.8 Landmarks
3.5 Pager		*.9 Device mgr.
3.6 Offline	9. Organiser	*.0 Help
	9.1 Calendar	*.*About
4. Browser	9.2 Clock	
	9.3 Notes	#. Settings
5. Log	9.4 Quickoffice	#.1 General
5.1 Recent calls	9.5 Calculator	#.2 Phone
5.2 Call duration	9.6 Converter	#.3 Connection
5.3 Packet data	9.7 File mgr.	#.4 Applications
	9.8 Memory	

Google

You can access Google and use the followings; Search, Maps, Blogger and YouTube.

Search

You can search the web-pages in this menu.

Maps

You can access maps from your mobile devices with this option.

Mail

You can receive or send e-mail. For details, please contact your service provider.

YouTube

You can view your friends' Youtube pages or log into your own and manage your postings.

Multimedia

RealPlayer

You can play sound or video clips saved in the phone or stream music and video clips.

► Open

- **Most recent clips:** Select this to play one of the up to 6 music or video clips you most recently played.

- **Saved clip:** Select this to play a saved video clip or to open a stream link to a media clip.

► **Download videos:** You can download video clips from the web.

► **Settings:** You can change video or connection settings.

► **About application:** You can view info about the application.

Music player

You can play music tracks.

<Key operations>

Key	Description
 / 	Starts playing music.
	Decreases the volume.
	Increases the volume.
 / 	Rewinds the track.
	Stops playback
 / 	Fast fwds the track.

► **Music library:** You can view, play and manage all music tracks saved on your device or memory card.

► **Open 'Now playing':** You can view the currently playing set of tracks.

► **Download tracks:** You can download music from the web.

► **Random play:** You can play music tracks in a random order.

► **Loop:** You can repeatedly play music, either a specific track or all tracks.

Multimedia

- ▶ **Equaliser:** You can enhance or diminish frequencies during music playback.
- ▶ **Add to track list:** You can add the playing music track to a new or saved track list.
- ▶ **Use tone**
 - **Set as ringing tone:** You can set the music track as the ringing tone for the current profile.
 - **Assign to contact:** You can set the music track as ringing tone for a contact.
- ▶ **Play in background:** You can leave **Music player** on in the background when using other applications.
- ▶ **View details**

Recorder

You can record speech or sound.

You can record a phone call by selecting **Recorder** during the call.

Note

- ▶ *Obey all local laws governing the recording of phone calls. Both parties of the call hear a tone every 5 seconds during recording.*

1. Press the left soft key [Options] and select **Settings** to select the recording quality and default memory for your sound clips.
2. Press the left soft key [Options] and select **Record sound clip** to start recording. When a recording is started, the recording time appears on the LCD.
3. When you finish the recording, press the right soft key [Stop]. The recorded file is automatically saved in **Sound clips** folder in **My stuff**.
4. To play the sound clip after recording, press **OK**.
5. You can listen to previously recorded sound clips by selecting **Go to My stuff**.

Camera

In this application, you can take photos or record videos.

You can switch between camera and video recorder using the right/left navigation keys.

To take photos:

1. The viewfinder shows you the image to be captured.
2. To zoom in/out, press the up/down navigation key.
3. Using the left soft key [Options], the followings are available.
 - ▶ **Capture:** Select this to take a photo.
 - ▶ **Show toolbar:** After selecting this, you can switch between **Image** and **Video** modes, activate night or sequence mode, or switch between main and secondary camera using the .
 - ▶ **Video mode:** Switches to **Video** mode.

- ▶ **Use secondary camera:** Select this to use the secondary camera.
- ▶ **Night mode:** You can activate/deactivate the night mode.
- ▶ **Sequence mode:** You can take multiple photos in one go by selecting **On**.
- ▶ **Self-timer:** To take a photo automatically after a short time delay.
- ▶ **Go to My stuff:** To view images and videos saved on the phone or memory card.
- ▶ **Adjust:** You can adjust the brightness, contrast, white balance and colour tone.
- ▶ **Settings**

Image

- **Image quality:** You can adjust the image quality.

Note

- ▶ *The better the image quality, the more memory the photo uses and the fewer photos you can save on your phone or memory card.*

Multimedia

- Show captured image:
Select **No** to take one photo immediately after another. This way, your photos do not remain on the display after you take them, and the camera is ready for use again.
 - Resolution (Camera 1): Select the desired resolution for the external camera by pressing **OK**.
 - Resolution (Camera 2): Select the desired resolution for the internal camera by pressing **OK**.
 - Default image name: To key in the default name for your new photos.
 - Memory in use: where to save your photos.
- **Help:** Use this option to get to know the phone feature.

► **Exit**

<Short-cut keys>

- 1'** : To activate night mode and take photos when lighting is dim

and the camera needs a long exposure time.

3[#] : To edit brightness settings.

4^s : To activate sequence mode and take 6 photos in one go.

6[^] : To edit contrast settings.

4. To take a photo, press **OK**. Photos are automatically saved in **Images** folder in **My stuff**.

To record videos:

1. Press right navigation key to switch to video camera.
2. To zoom in/out press up/down navigation key.
3. Using the left soft key [Options], the followings are available:
Record, Show toolbar, Image mode, Use secondary camera, Night mode, Mute, Go to My stuff, Adjust or Settings.

Video

- Length: Select between **Maximum** and **Short**.

Tip

► *To send the video clip in a multimedia message, select **Short** to reduce the size of the video.*

- Resolution (Camera 1): Select the desired resolution for the external camera by pressing .
- Resolution (Camera 2): Select the desired resolution for the internal camera by pressing .
- Default video name: To key in the default name for your new videos.
- Memory in use: Select where to save your videos.
- **Help:** Use this option to get to know the phone feature.
- **Exit:** Exits the application.

4. To record a video, press .
5. To stop recording, press the right soft key [Stop]. Videos are automatically saved in **Video clips** folder in **My stuff**. if you do not want to save the video press .

To play the video, press the left soft key [Options] and select **Play**.

Flash Player

You can view and play Flash files made for mobile devices.

1. To open a folder or play Flash file, scroll to the folder of file and press .
2. Scroll to a Flash file and press the left soft key [Options].

Note

► *Available options may vary.*

- **Send:** You can send the Flash file to compatible devices.
- **Organise**
 - **Copy to folder:** To save a copy of the file in another folder.
 - **Move to folder:** To move the file to a different folder.
 - **New folder:** To create a folder to organize your Flash files.
- 3. To delete a Flash file, scroll to it and press .

Profiles

You can manage the call, message, and other alert settings of your phone.

1. To change the profile, scroll to the desired profile, press the left soft key [Options] and select **Activate**.

Note

- ▶ To change profiles in any view, briefly press the Power key on the right side of the phone.
- ▶ To quickly activate the Silent profile in standby mode, press and hold . To return to General profile, again press and hold .
- ▶ In Offline profile, you cannot make or receive calls or use other features that require network coverage.

2. To modify a profile, scroll to it, press the left soft key [Options], and select **Personalise**.

Scroll to the following settings and  to edit: Ring tone, Video call tone, Ring type, Ring volume, Message alert tone, E-mail alert tone, Vibrating alert, Keypad tones, Warning tones, Alert for.

Tip

- ▶ When you select **Ascending**, the ringing volume starts from level one and increases level by level to the maximum volume you set in the next setting.

To save your settings, press **Back**.

3. To create a new profile with your own sound settings, press the left soft key [Options] and select **Create new**.

Browser

Browsing the web

You can browse web pages in this menu. Key in the page address and press the left soft key [Go to].

Keyboard shortcuts:

 / 	To Open your B ookmark
 / 	To search for specific text on the page(F ind)
 / 	To return to the P revious page
 / 	To switch between your open W indows
 / 	To toggle page O verview on and off
 / 	To G o to a different web page.
 / 	To goto your H omepage

You can access the followings by pressing the left soft key [Options]: **Open link, Go to web address, Bookmarks, Save as bookmark, Rotate screen, Navigation options, Zooming options, Window, Clear privacy data, Tools, Find, Settings.**

Tip

► *Cookies are necessary if you shop on the web to retain the items you buy until you reach the cashier page, for example. However, the info may be misused, and you may receive unwanted advertisements in your phone, for example.*

Saved pages

You can view a saved web page. After scrolling to it, press .

Scroll to a saved page and press the left soft key [Options] to access the followings: **Saved pages, Clear privacy data.**

To remove a saved page, scroll to it and press .

Browser

Auto. Bookmarks

You can return to a web page you have recently visited. After scrolling to the desired page address, press .

Scroll to a bookmark and press the left soft key [Options] to access the followings: **Back to page, Bookmark manager, Mark/Unmark, Navigation options, Clear privacy data, Tools, Details, Settings.**

To delete a bookmark, scroll to it and press .

Note

- The NDTV midlet shortcut is present under Browser -> options.

Browser feeds

You can download and manage feeds and blogs.

Blog is short for weblog, which is a continuously updated web diary meant to be viewed by any web user.

To download a feed or blog, scroll to it and press .

You can access the following by press the left soft key [Options]: **Refresh, Refresh all, Manage feed, Mark/Unmark, Back to page, Clear privacy data, Settings.**

Log

Log

Recent calls

You can view the recently missed, received and dialed calls.

Missed calls

Allows you to view the last 20 phone numbers from which someone unsuccessfully tried to reach you.

Received calls

Allows you to view the last 20 phone numbers that you have answered.

Dialled numbers

Allows you to view the last 20 phone numbers that you have called or tried to call.

Note

► You can also view Dialled numbers in standby mode by pressing .

You can make a call, send a message and save the number in Contacts. You can edit the phone number or copy the number using **Use number** option. You can delete your missed, received, or dialled calls.

You can reset the recent calls register in **Recent calls**, press the left soft key [Options] and select **Clear recent calls**. To set the time period to keep log events in the phone memory, select **Settings** option.

Call duration

You can view the duration of calls to and from your phone.

Using the left soft key [Options], the followings are available: **Clear timers**, **Settings**, **Help**, **Exit**.

Packet data

You can check the amount of data transferred during packet data connections.

Note

► You may be charged for your packet data connections according to the amount of transferred data.

Using the left soft key [Options], the followings are available: **Clear counters**, **Settings**, **Help**, **Exit**.

Messaging

New message

You can create a text message, multimedia message, audio message or E-mail. Press the left soft key [Options]. You can access the followings.

Create message

You can create Text message/ Multimedia message/ Audio message/ E-mail.

Text message

1. In the **To** field, press **[OK]** to select recipients from Contacts or key in a recipient mobile phone number.
2. Move to the message field by pressing the down navigation key.
3. Enter your message in the message field.

Option menus in message field:
Add recipient, Insert, Sending options, Message details, Writing language.

4. Press **[Send]** to send the message.
The messages will automatically be saved in the Sent message folder.

If the message has not been sent, it will remain in the Outbox with a failed status.

Note

- To save the message without sending it, press the right soft key [Close] and select **Save to Drafts**.

Multimedia message

Multimedia messages may contain text, images and sound and video clips. To send and receive multimedia messages, you need to register with a multimedia messaging service and define multimedia settings in your phone.

1. In the **To** field, press **[OK]** to select recipients from Contacts or key in a recipient mobile phone number or an e-mail address.

Tip

- If you key in more than one number, separate the numbers with a semicolon. To insert a semicolon, press **[Chr]** and select **;** using the navigation keys.

- ▶ To add @ in letter mode, press and hold  and press .

2. Enter a subject in the **Subject** field.
3. Enter your message in the message field.

Option menus in message field

(Note: Available options may vary.): **Send, Add recipient, Create presentation, Insert object, Insert new, Place text first/ Place text last, Remove, Address fields, Preview, Objects, Check contacts, Sending options, Message details, Writing language, Help, Exit.**

4. Press  to send the message.

Audio message

1. Press  to record your message.
2. When you hear a sound, please start recording.
(You can record up to 2 minutes and 30 seconds.)
3. To save the sound clip, press the left soft key [Options] and select **Save sound clip**.

Note

- ▶ You can check what you recorded using **Play sound clip** option.
 - ▶ To replace the sound clip, select **Replace sound clip** → **New sound clip**.
 - ▶ To send a sound clip in your phone or memory card, select **Replace sound clip** → **From My stuff**. Scroll to the desired music track or sound clip and press .
 - ▶ To delete the audio clip, press .
4. Scroll to the **To** field. Press  to select recipients from Contacts or key in a recipient mobile phone number.

Tip

- ▶ If you key in more than one number, separate the numbers with a semicolon. To insert a semicolon, press  and select ; using the navigation keys.
5. Press  to send the message.
Audio messages are transferred in the multimedia messaging service.

Messaging

E-mail

To send/receive an email, you should set up the email account.

1. In the **To** field, press  to select recipients from Contacts or key in an e-mail address.

Tip

- ▶ If you key in several addresses, separate them with a semicolon. To insert a semicolon, press  and select ; using the navigation keys.
- ▶ Insert the primary recipients in the **To** field and those who only need the e-mail for reference in the **Cc** field.

2. Enter a subject in the **Subject** field.
3. Enter your message in the message field.

Option menus in message field

(Note: Available options may vary.): **Add recipient, Insert, Address fields, Attachments, Sending options, Writing language, Help, Exit.**

4. Press  to send the message.

Note

- ▶ To save the message without sending it, press the right soft key [Close] and select **Save to Drafts**.

SIM messages

You can browse messages on your SIM card.

Cell broadcast

With the cell broadcast service (CBS), you can receive informative messages from your service provider on various topics, such as weather or traffic conditions in a particular region.

To receive cell broadcast messages, you need to turn on cell broadcast reception.

Press the left soft key [Options] and select **Settings**. Set the **Reception On**.

In the Cell broadcast topic list, the followings are available by pressing the left soft key [Options]: **Open, Subscribe, Hotmark, Topic, Settings**.

Service commands

You can send service commands such as activation requests for network services, to your service provider. After keying in a command and press .

Settings

You can define or edit settings for different message types. For further information, please refer to the Help menu on the phone.

Inbox

You can browse, open and manage received text, multimedia and other messages.

1. Scroll to a new message and press .
2. Using the left soft key [Options], the followings are available. (Note: Available options may vary): **Create message, Reply, Sort by, Move to folder or Mark/Unmark.**

To delete a message, press .

To call the sender of the message, press .

Note

- You can view other folders in **Messages** by using the left/right navigation keys.

My folders

You can view messages or message templates saved in your own folders.

Mailbox

You must register for an e-mail service and set up a mailbox to receive/send emails.

Contact your service provider for correct settings.

In the e-mail list, the followings are available by pressing the left soft key [Options].

(Note: Available options may vary): **Create message, Connect, Retrieve e-mail, Delete, Sort by or E-mail settings.**

Messaging

Drafts

You can view, edit and send messages you have created but not yet sent.

1. Press  to view or edit a message.
2. To send a message, press .
3. To delete a message, scroll to it and press . You can delete multiple messages. [Options] and select **Mark/Unmark** to put a tick next to it. Once you have marked the desired messages, press .

Sent

Your last 20 sent messages are automatically saved in the **Sent** folder. The following options are available using the left soft key. (Note: Available options may vary) **Sort by** or **Move to folder**.

Outbox

You can view and manage messages waiting to be sent.

1. To cancel sending a message, use the following options after pressing the left soft key [Options]: **Defer sending, Delete, Move to Drafts**.
2. To send a message that is suspended, failed or scheduled for later delivery, press the left soft key [Options] and select **Send**.

Reports

You can keep track of your text and multimedia messages after sending. You can call a message recipient by pressing the .

Note

- You can receive or reject delivery reports in text and multimedia message settings. (Open Messages and press the left soft key [Options] and select **Settings** → **Text messages** or **Multimedia message**. Set **Receive report** to **Yes/No**.)
- No delivery reports can be received from messages sent to e-mail addresses.

Contacts

New contact

You can create a contact address. You can enter the first name, last name, mobile number, telephone number, E-mail address, a number for video call, pager number, company name and job title of a new contact. You can add, rename or delete contact card fields, using **Add detail**, **Edit label** or **Delete detail** options. After filling in the fields, press the right soft key [Done].

Contacts list

You can view a contact card by pressing the .

To make a voice or video call to a contact, press .

Using the left soft key [Options], the followings are available: **Open**, **Call**, **Create message**, **Edit**, **Delete**, **Duplicate**, **Mark/Unmark**, **Copy to SIM directory**, **SIM contacts**, **Send business card**, **Contacts info**, **Synchronisation** → **Start**,

Synchronisation → **Settings**, **Settings**, **Help**, **Exit**

To remove a contact from the directory, press the .

Groups

Press the right navigation key in Contact list.

You can create contact groups to send messages to a number of people at the same time, for example.

Using the left soft key [Options], the followings are available: **Open**, **Create message**, **New group**, **Delete**, **Rename**, **Ringtone**, **Contacts info**, **Settings**, **Help**, **Exit**.

To delete a contact group, press the . The individual contacts cards of group members remain in the Contacts directory.

Connectivity

Conn.mgr.

You can manage active data connections.

To view detailed connection info, such as the duration, speed of data transfer, and the amount of data sent or received, scroll to the connection and press **OK**.

To end a connection, scroll to it and press **↵**.

To end all connections, press the left soft key [Options] and select **Disconnect all**.

Bluetooth

You can make a wireless connection to other compatible devices such as computers.

Bluetooth provides you with wireless connections to other Bluetooth devices such as computers or other phones.

- ▶ **Bluetooth:** To enable wireless connections to other Bluetooth devices, select **On**.

- ▶ **My phone's visibility:** Set the visibility of your phone to other Bluetooth devices.

Note

- ▶ Your **Paired devices** can still connect to your phone even if you select **Hidden**.
- ▶ **My phone's name:** You can change the name of your phone, which is visible to other devices that search for Bluetooth devices. Key in the new name and press **OK**.

To send data via Bluetooth:

1. Open the application that contains the item you want to send.
2. Scroll to the item, press the left soft key [Options] and select **Send → Via Bluetooth**.
3. The phone searches for Bluetooth devices within range and lists them.

Scroll to the desired device and press **OK** to set up the connection.

To pair with a device:

1. Press the right navigation key to move to the **Paired devices** window.
2. Press the left soft key [**Options**] and select **New paired device**. The phone starts to search for Bluetooth devices within range.
3. Scroll to the device with which you want to pair and press **OK**.
4. Agree on a common passcode with the owner of the other device and key it in. Press **OK**.

Note

► *Some devices have fixed passcodes.*

If you trust a paired device, you can allow it to connect automatically to your phone. Scroll to the device, press the left soft key [**Options**] and select **Set as authorised**. This way, you do not have to accept a device manually every time you connect to it.

To give a nickname to a paired device that is displayed only in your phone, scroll to the device, press the left soft key [**Options**], and select **Assign short name**.

To delete pairing with a device, scroll to the device and press **↵**.

USB

You can transfer data to and from another device using the USB wire provided in the sales pack.

You can change the device type to which you normally connect your phone with the USB cable.

USB mode

- **PC Suite:** To connect PC Suite to your phone via the USB cable.
- **Data transfer:** To access and transfer data, such as text or music files, between your memory card and a compatible device, such as a computer, using USB.

Connectivity

Ask on connection

Select **Yes** to select the **USB mode** every time you use the USB cable to connect your phone to another device.

Sync

You can synchronise data in your phone's contacts, calendar, notes and text message applications with corresponding applications on a computer or Internet server. Synchronisation settings are saved in sync profiles.

Note

- *The available applications you can synchronise may vary. Contact your service provider for more information.*

Scroll to a sync profile and press the left soft key [Options]. You can access the followings. **Synchronise**, **Edit sync profile**, **New sync profile**, **View log**.

To delete a synchronization profile, scroll to it and press .

Organiser

Calendar

You can edit and keep track of your schedule.

Using the left soft key [Options], the followings are available. **Open, New entry, Week view, To-do view, Delete entry, Go to date, Settings.**

Tip

► You can also add appointments by starting to write with the number keys. The **Meeting** editor opens automatically.

Clock

Time

You can view the time, day of the week and date, or set and edit alarms or modify date and time settings.

1. To set date and time, press the left soft key [Options] and select **Settings**.
2. Scroll to the following settings and press **OK**: **Time, Time zone, Date, Date format, Date separator, Time**

format, Time separator, Clock type, Alarm clock tone, Workdays, Network operator time.

Note

► This service may not be available in all networks.

3. Press the right soft key [Back] to save your settings.

To quickly set a one-time alarm, press any number key and key in the alarm time. To change the time of a set alarm, press the left soft key [Options] and select **Reset alarm**.

Alarm

1. In the **Clock** window, press the right navigation key.
2. Press the left soft key [Options] and select **New alarm**.
3. Fill in the following fields. **Alarm time, Description, Repeat**.
4. Press the left soft key [Done].

Organiser

Tip

- ▶ To quickly set a one-time alarm, you can also press any number key and key in the alarm time.

To deactivate or delete an alarm, scroll to it and press .

World

1. In the **Clock** window, press the right navigation key twice.
2. Press the left soft key [Options]:
Add city, Set as the current city, Settings.
3. To delete a city, scroll to it and press .

Notes

You can view or write notes.

1. To write a note, press any number key. The note editor opens automatically.

Tip

- ▶ To add a space between words, press .

- ▶ To insert special characters, press .

2. To save your note, press the right soft key [Done].
3. Using the left soft key [Options], the followings are available: **Open, Send, New note, Delete, Mark/Unmark, Synchronisation.**

Quickoffice

Shows compatible files in the Documents folder in phone memory and/or the memory card.

The application tabs determine which types of documents are displayed.

- ▶ **Quickword:** Microsoft Word and text documents.
- ▶ **Quicksheet:** Microsoft Excel spreadsheets.
- ▶ **Quickpoint:** Microsoft PowerPoint presentations.
- ▶ **Quickmanager:** To update and upgrade your Quickoffice software and download other useful applications.

Using the left soft key [Options], the followings are available. **New file, Sort by, Details, Send.**

Calculator

To use the calculator:

1. Key in the first number of the calculation.
2. To select a function on the right-hand side of the display, scroll to it and press the .
3. Key in the next number of the calculation.
4. Select any remaining operations and key in numbers.
5. To execute the calculation, scroll to "=" and press .
6. The result of the calculation remains in the editor field and can be used as the first number of a new calculation.

Converter

You can convert **Currency, Area, Energy, Length, Mass, Power, Pressure, Temperature, Time,**

Velocity and Volume from one unit (for example, gallons) to another (litres).

File mgr.

You can browse and manage folders and files.

1. To view the contents of a folder or file, scroll to it and press .
2. To send a file to compatible devices, scroll to it and press .
3. Using the left soft key [Options], the followings are available: **Move to folder, Copy to folder, New folder, Mark/Unmark, Rename, Find, View details, Memory details.**

Note

- Default folders such as **Sound clips** in **My stuff** cannot be moved or deleted.
- 4. To delete a folder or file, scroll to it and press .

Note

- To browse and manage folders and files on your memory card, press the right navigation key.

Organiser

Memory

You can view the status of the memory card. Using the left soft key [Options], the followings are available: **Remove memory card**, **Back up phone memory**, **Restore from card**, **Format memory card**, **Memory card name**, **Set password**, **Memory details**.

Note

- ▶ *Do not format a memory card that contains important software or data as formatting destroys all that is saved on the card.*

Tip

- ▶ *You can select Remove password later. This means the memory card is unlocked and no password is requested when it is inserted into another device. In this case, the data saved on the card is not protected against unauthorised use.*

My stuff

You can browse media files in each folder.

Images

Images contains a folder of default images and default flash files pre-loaded onto your phone, images downloaded by you and images taken on your phone's camera.

- ▶ **Download:** You can download images from the web.
- ▶ **Send:** You can send the image via MMS, Bluetooth or Email.
- ▶ **Find:** To find a particular image, key in the first letters of the image name. You can send an image to compatible devices by pressing the .
- ▶ **Sort by:** You can arrange your images according to their date, title, size, format.
- ▶ **Use image**
 - **Set as wallpaper:** You can set the image as the background image for the display while the phone is in standby mode.
 - **Add to contact:** You can add a thumbnail image to a contact card.
- ▶ **Delete:** Delete a file
- ▶ **Organise**
 - **New folder:** You can create a folder to store images.
 - **Move to folder:** You can move the image to a different folder.
 - **Copy to memory card/ Copy to phone mem.:** To copy the image or folder to your memory card or phone memory.
 - **Move to memory card/ Move to phone mem.:** To move the image or folder from one memory to another.
- ▶ **Mark/Unmark:** You can select multiple images for sending or deleting at the same time, for example.
- ▶ **Rename:** Change the file name.
- ▶ **View details:** You can view detailed information on the image.

My stuff

Video clips

The **Videos** folder shows the list of downloaded videos and videos you have recorded on your phone: **Download, Send, Find, Sort by, Delete, Organise, Mark/Unmark, Rename, View details.**

Tracks

Music albums are automatically created based on the ID3 tags attached to the music files.

You can allow or prevent the display of these albums using **Show albums/Hide albums** option: **Download, Send, Find, Sort by, New track list, Use tone, Edit, Organise, Show albums/Hide albums, View details, Mark/Unmark, Delete.**

Note

- If you delete M3U files by using **New track list** option, the contained tracks are not deleted. If you delete an item shown using the **Show album** option,

every track the album includes will be deleted.

Sound clips

The **Sounds** folder contains the **Default sounds**, your voice recordings and sound files downloaded by you. From here you can manage, send or set sounds as ringtones: **Download, Send, Find, Sort by, Use tone, Organise, View details, Mark/Unmark.**

Streaming links

To use a link to play the media file, scroll to the link and press **OK**: **Send, Find, New link, Edit, Organise, Mark/Unmark**

Note

- *Streaming means playing music, video, or sound clip files directly from the web, without first downloading it to your phone.*

Presentations

Presentations may contain SVG -T and Flash file presentations, which combine multiple media files, such as images and sound clips. Presentations may also be interactive. To play a presentation scroll to it and press **OK**. You can adjust the volume using **⏮** on the left side of the phone. To delete a presentation, scroll to it and press **⏮**: **Find, Sort by, Organise, Mark/Unmark**.

All files

You can view or play a media file or streaming link to a media file by pressing **OK**: **Find, Sort by, Organise, Mark/Unmark, Rename**.

Note

- ▶ *Not available for links. You can rename links using **Edit** option.*

Tools

Installations

Applications are installed automatically with your phone start.

Call mailbox

You can use the network service of voice mail that works as an answering machine for your phone. A call mailbox is a network service that works as an answering machine where people who are unable to reach you can leave messages.

Tip

- ▶ *With the call diverting network service, you can direct incoming calls to your call mailbox. [Menu → Settings → Phone → Call divert → Voice calls]*

If your phone prompts you for the call mailbox number that you cannot recall, press the left soft key [Find] to search for it in **Contacts**.

Tip

- ▶ *To quickly call your call mailbox in standby mode, press **[1']** and **[↩]**.*

Using the left soft key [Options], you can access the followings. **Define number, Call voice mailbox, Change number.**

Speed dial

You can assign speed dialling keys (from **[2^e]** to **[9']**) to phone numbers in your contacts directory.

Some number keys may be assigned as speed dials to special phone numbers. For example, number **[1']** is reserved for your call mailbox.

To assign speed dialling keys:

1. Scroll to an available speed dialling number and press **[OK]**.
2. Select **Assign**.
3. Select the contact to whom you want to assign the speed dial. Select the phone number.

You can call a phone number linked to a speed dialling key in standby mode by pressing the speed dial and then **[↩]**.

Note

- *To call a number linked to a speed dialling key just by pressing and holding the speed dial in standby mode, open **Settings** → **Phone** → **Call** → **Speed dialing** and select **On**.*

To assign a speed dialling key to a different phone number:

1. Scroll to the speed dialling number and press the left soft key [Options].
2. Select **Change**.
3. Select the new contact and number.

You can remove a number linked to a speed dial by pressing the left soft key [Options] and selecting **Remove**.

The contact and phone number you remove will remain in your **Contacts**.

Themes

You can change the look of your phone's display. In Themes, you can select different themes, which consist of various settings that affect the appearance of your phone's display.

Some themes may also include ringtones or message alert tones.

General

You can preview or change the theme used for all applications that do not have their own themes or download more themes to your phone.

Menu view

You can change the display appearance of applications in **Menu** between **Grid** and **List** formation.

Wallpaper

You can change the background image on the display in standby mode. To change the background image on the display in standby mode, scroll to Image and press .

Power saver

You can change the option that appears as power saver when your device has been idle and no keys have been passed for some time: **Date and time**, **Text** or **Animation**.

Tools

Tip

- ▶ You can key in the Power saver timeout after which the power saver is turned on, in **Menu** → **Settings** → **General** → **Personalisation** → **Display**.

Note

- ▶ You can also choose any other power saver you may have installed on your phone.

Using the left soft key [Options], you can access the followings: **Preview**, **Settings**.

Actv. keys

You can view and manage usage rights for media files in your phone. Some media files, such as images, music or video clips are protected by digital usage rights.

The activation keys for such files may allow or restrict their usage. For example, with some activation keys you may listen to a music track only a limited number of times. During one

playback session you may rewind, fast-forward or pause the track, but once you stop it, you have used one of the instances allowed.

Valid keys

To view detailed info about your usage rights for a media file, such as their validity status and whether you can send the media file to other devices, scroll to the corresponding activation key and press **OK**.

Tip

- ▶ In the activation key details view, you can see the validity status of the key, details about your usage rights and restrictions for the corresponding media file and where the media file is currently saved on your device.

Using the left soft key [Options], you can access the followings. **Get new key**, **Reload**

To delete the activation key for a media file and the media file itself, scroll to the key and press **↵**.

Invalid keys

To view detailed info about your expired or missing usage rights for a media file, scroll to the corresponding activation key and press **OK**.

Tip

- ▶ *Activation keys expire when you run out of instances when you are allowed to use a media file or the time period for using the file ends.*
- ▶ *In the activation key details view, you can see the validity status of the key, details about your usage rights and restrictions for the corresponding media file and where the media file is saved on your device.*

Using the left soft key [Options], you can access the followings. **Get new key, Reload.**

Note

- ▶ *You may not be able to buy more instances or extend the usage period for all media files.*

Not in use

Unused activation keys are usually for media files that have been deleted from the device or saved on a removed memory card. To view detailed info about an activation key not in use, scroll to it and press **OK**. Using the left soft key [Options], you can access the followings.

Reload, Restore activation keys.

App. mgr.

You can install and update Java and other applications or components compatible with the Symbian operating system.

You can receive software installation packages via e-mail or multimedia messaging, transfer them from a computer or download them from the Web.

To download and install software from the Web, select **Download apps**.

Tools

Scroll to an application and press the left soft key [Options] to access the followings: **Install, Open, View details, Send, Remove, View log, Settings**

GPS data

Note

- *For the GPS data application to function correctly, a satellite-based positioning method must be in use. To select the positioning method used to detect the location of your device, press Option → Positioning settings.*

Navigation

You can view navigating info to your trip destination. Duration provides you with an estimate of the remaining time before you reach your destination at your current travelling speed.

Tip

- *The top of the display must point in the direction you are moving for the direction to your destination to remain valid.*

Using the left soft key [Options], you can access the followings: **Set destination, Stop navigation, Save position, Satellite status.**

Position

You can view positioning info, such as the latitude and longitude coordinates and the altitude of your current location. You can also see the accuracy of this info.

Using the left soft key [Options], you can access the followings: **Save position, Satellite status.**

Trip distance

You can view your travelling info, such as the distance, duration you have travelled, your average speed and maximum speed.

Using the left soft key [Options], you can access the followings: **Start, Stop, Resume, Reset, Restart, Clear, Satellite status.**

Note

- *The GPS data application must receive positioning info from at least 3 satellites to function as a travelling aid. If the satellite signal is lost during the trip, the trip distance values you can see are not current, but based on the latest positioning info available.*

Landmarks

You can map particular locations in your device and make it easy to find them.

Using the left soft key [Options], you can access the followings: **Edit, New land mark, Delete, Add to category, Send, Call, Go to web address, Mark/Unmark, Edit categories, Landmark icon.**

Device mgr.

To view or update the current software version of your device.

Using the left soft key [Options], you can access the followings:

Install update, Check for updates, Settings.

Note

- *Before the installation, make a backup of the data in your device, and check that the device battery has enough power or connect the charger.*

Help

You can read instructions about using the applications and functions of your phone.

About

You can see the copyright information of this product.

Settings

General

You can edit the general settings of your device or restore the original default device settings.

Personalisation

To edit settings related to the display, standby mode and general functionality of your device.

- ▶ **Display:** You can edit brightness, list font size and other display settings. After setting each value, press the right soft key [Back]: **Brightness, List font size, Power saver time-out, Welcome note / logo or Light time-out.**
- ▶ **Standby mode:** To select the general theme for your device, edit the theme settings and display or hide the operator logo. **Active standby, Shortcuts or Active standby apps.**
- ▶ **Tones:** To edit settings for the various sounds produced by your phone.

- ▶ **Themes:** To change the look of your device's display.

Note

- ▶ **Language:** To select the languages for the phone texts and for you to write messages, notes and other texts.

Date and time

To edit time and date settings.

Enhancement

You can edit settings related to the various enhancements such as **Headset** and **Wireless car kit** you can use with your device.

- ▶ **Headset:** Default profile, Automatic answer.
- ▶ **Wireless car kit:** Default profile, Automatic answer.

Security

You can edit settings related to the security of your personal information on your phone or SIM card and data

connections between your device and the network.

- ▶ **Phone and SIM card:** To change the PIN and other security codes and edit other security settings for your phone and SIM card: **PIN code request, PIN code, PIN2 code, Keypad autolock period, Phone autolock period, Lock code, Lock if SIM card changed, Confirm SIM services.**
- ▶ **Certificate management**
To view and manage the digital certificates in your phone.
- ▶ **Security module**
To view or edit security modules.

Factory settings

To restore the default settings of your device or remove any operator settings, press the left soft key [Yes] and key in the lock code.

Note

- ▶ *Default lock code is 12345.*

Positioning

The location of your device can be detected and the info can be used by other applications in your device.

Phone

You can edit the general settings related to making and receiving calls.

Call settings

- ▶ **Send my caller ID:** Scroll to **Yes** to display your caller identity to the people you call, **No** to hide it or **Set by network** to follow the default setting of your home network.
- ▶ **Call waiting:** To be notified of incoming calls while you have a call in progress, select **Activate**.
- ▶ **Reject call with SMS:** To send an explanatory text message to callers when you reject their call, select **Yes**.
- ▶ **Message text:** Key in the text for the message to send to rejected callers.

Settings

- ▶ **Image in video call:** To send a still image to video callers if you disable sending your video during the calls.
- ▶ **Automatic redial:** To have your phone redial when numbers are busy or calls are not answered, select **On**.
- ▶ **Show call duration:** To have the length of a call displayed during the call, select **Yes**.
- ▶ **Summary after call:** To have the duration of a call briefly displayed after the call, select **On**.
- ▶ **Speed dialling:** To call the phone numbers to which you have assigned speed dialling keys by pressing and holding the speed dial key, select **On**.
- ▶ **Anykey answer:** To answer incoming calls by pressing any key except the End and Power keys, select **On**.
- ▶ **Line in use (shown if ALS is supported by SIM):** Select either of your phone lines as the primary line for making calls and sending messages.

- ▶ **Line change (shown if ALS is supported by SIM):** To prevent the primary line from being changed, select **Disable**. You need your PIN2 code to change this setting.

Note

- ▶ *The accessibility of some Call settings depends on the availability and your subscription to the network services. Contact your service provider for more information.*

Call divert

You can divert incoming calls to your voice mailbox or to another phone number.

- ▶ **Voice calls:** You can divert incoming voice calls to your voice mailbox or to another phone number. Select **Activate** → **To voice mailbox** or **To other number**.

To cancel the diverting of calls, scroll to the active divert options, press the left soft key [Options] and select **Cancel**.

To check your current diverts, scroll to the call divert options, press the left soft key [**Options**] and select **Check status**.

- ▶ **Data and video calls:** You can divert incoming data and video calls to another phone number.

Call barring

You can restrict the receiving of calls: **Outgoing calls/ International calls/ International calls except to home country/ Incoming calls/ Incoming calls when abroad**.

To edit mobile call barring settings, you need a password. You obtain the barring password from your service provider upon subscription to this network service. Call barring affects all voice and data calls, except emergency calls. Scroll to barring options, press **OK** and select:

- ▶ **Activate** to restrict calls.
- ▶ **Cancel** to undo call restriction.
- ▶ **Check status** to see if calls are restricted or not.

Network

You can select the network type, the manner of selecting networks and indicate when your phone is used in a Micro Cellular Network: **Network mode, Operator selection, Cell info display**

Connection

You can edit access point and other connection settings.

Bluetooth

You can edit settings for Bluetooth connectivity. For further information.

Bluetooth provides you with wireless connections to other Bluetooth devices such as computers or other phones: **Bluetooth, My phone's visibility, My phone's name**.

Tip

- ▶ *Give a unique name to your phone to make sure it is easy to recognise when there are several Bluetooth devices in the vicinity.*

Settings

USB

You can change the device type to which you normally connect your phone with the USB cable. **USB mode, Ask on connection.**

Access points

You can view, create, and manage access points. An access point is where your phone connects to the network by way of a data call or packet data. To use e-mail and multimedia services or to browse web pages, you must first define internet access points for these services.

1. To create a new access point, press the left soft key [**Options**] and select **New access point**.
2. Scroll to the following settings and press **OK** to edit: **Connection name, Data bearer, Dial-up number, User name, Prompt password, Password, Authentication, Homepage, Data call type, Maximum data speed.**

3. To save your settings, press the right soft key [Back].

The icons on the left-hand side of the access points indicate their data bearers.

To edit an access point, scroll to it and press **OK**.

To delete an access point, scroll to it and press **←**.

Note

- *For further information, please refer to the Help option on the handset.*

Packet data

You can set when to use packet data connections and key in the access point to be used if you use your phone as a modem for a computer.

- **Packet data connection:** Define when to use packet data connections.
- **Access point:** If you use the phone as a modem to enable packet data connectivity from a computer, scroll to this and press **OK**. Key in the access point name and press

OK. Contact your service provider for the access point name for modem connections.

To save your settings, press the right soft key [**Back**].

SIP settings

You can create or edit session initiation protocol (SIP) profiles, which are necessary for making Internet calls.

To create a SIP profile, press the left soft key [**Options**] and select **New SIP profile** → **Default profile** or **Use default profile** to select a profile as the basis for the new profile.

To edit a SIP profile, scroll to it and press .

To select the SIP profile you want to use by default for communications sessions, scroll to the profile, press the left soft key [**Options**] and select **Default profile**.

To delete a SIP profile, scroll to it and press .

Note

► SIP profiles may be preset in your device or you may receive them from your service provider. You may not be able to edit or manage SIP profiles.

Configurations

You can view or delete trusted servers from which your phone may receive configuration settings. You can receive messages from your network operator, service provider, or company information management department. These messages contain configuration settings for trusted servers and are automatically saved in **Configurations**. From trusted servers you may receive configuration settings for access points, multimedia or e-mail services, and synchronisation settings.

To delete configurations for a trusted server, scroll to the server and press . The configuration settings for other applications provided by this server are also deleted.

Settings

Note

- *For example, you may need to delete trusted server configurations and the configuration settings provided by it when you change your service provider.*

Applications

You can edit the settings of different applications.

RealPlayer

You can change RealPlayer video or connection settings:
Video, Streaming.

Camera

You can edit image or video settings. For further information, please refer to p.35-37.

Voice recorder

You can select the recording quality and default memory for your sound clips: **Recording quality, Memory in use.**

App. manager

You can edit the Application manager settings.

Some software packages that you install in your device may contain certificates for additional security: **Software installation, Online certificate check, Default web address.**

Log

You can set the time period to keep log events and to display call duration during calls.

Note

- *If you select **No log**, all log contents are permanently deleted.*


Tip

- *You may also edit the settings of other applications installed in your device by your service provider that appear on the list.*

Accessories

There are various accessories for your mobile phone. You can select these options according to your personal communication requirements.


Charger



Hands free ear-microphone and controller combo




Standard Battery



Data cable/CD

You can connect your phone to PC to exchange the data between them.



Note

- ▶ Always use genuine LG accessories.
- ▶ Failure to do so may invalidate your warranty.
- ▶ Accessories may vary in different regions: please check with our regional service company or agent for further information.

Technical data

Technical data

General

Product name : KT610

System : GSM 900 / DCS 1800 / PCS 1900 / W-CDMA

Ambient temperatures

Max : +55°C (discharging), +45°C (charging)

Min : -10°C

Declaration of Conformity



LG Electronics

Suppliers Details

Name

LG Electronics Inc

Address

LG Electronics Inc. LG Twin Towers 20,
Yeouido-dong, Yeongdeungpo-gu, Seoul, Korea 150-721

Product Details

Product Name

GSM 900 / DCS 1800 / PCS 1900 / W-CDMA Terminal Equipment

Model Name

KT610

Trade Name

LG

C E 0168

Applicable Standards Details

R&TTE Directive 1999/5/EC
EN 301 489-01 V1.6.1, EN 301 489-07 V1.3.1
EN 301 489-17 V1.2.1, EN 301 489-24 V1.3.1
EN 301 511 V9.0.2
EN 301 908-1 V3.2.1 EN 301 908-2 V3.2.1,
EN 300 328 V1.6.1
EN 50360/EN 50361:2001
EN 60950-1 : 2001

Supplementary Information

Declaration

I hereby declare under our sole responsibility
that the product mentioned above to which this
declaration relates complies with the above mentioned
standards and Directives

Name


Issued Date

Seung Hyoun, Ji / Director

18.Apr. 2008

LG Electronics Inc. Amsterdam Office
Veluwezoom 15, 1327 AE Almere, The Netherlands
Tel : +31 - 36- 547 - 8940, e-mail : seokim @ lge.com

Signature of representative





WARRANTY CARD

This LG handset and charger comes with a 12-month warranty from date of purchase or 15 months from manufacturing date of corresponding IMEI No. Of the unit whichever is earlier, against defect in material or workmanship. In case of a defect, LG Electronics India Pvt. Ltd. undertakes to get the set repaired free of charge through its authorised service centre (ASC) or service dealer subject to following conditions:

Terms and Conditions

1. This warranty is applicable to the first purchase and in no case it can be transferred or extended.
2. Repair of this product will be carried out on a carry in basis to the nearest ASC.
3. While the company will make every effort to carry out repairs at the earliest, it however is made explicitly clear that the company is under no obligation to do so in a specified period of time.
4. The company or its authorised ASC/ service dealer reserves the right to retain any parts of the component/s replaced at its discretion. In the event of a defect being noticed in the equipment during the warranty period.
5. This warranty entitles the purchaser to free of cost repairs of the unit within warranty period and does not entitle for replacement or refund of entire unit. Claims, if any, to this warranty shall in no case exceed the purchase price of the unit.
6. In case of any software upgradation of the phone, no warranty is provided on phone memory or phone book.
7. The warranty is void in case the serial no./ IMEI no. is tampered / disfigured or details in the warranty card are not properly filled up at the time of purchase.
8. This warranty is not valid for damages resulting due to negligence, mishandling, improper use, tampering, breakage, soaking, fire, unauthorised repair and failure due to network upgrades.
9. Batteries are covered under warranty for a period of 6 months from date of purchase or 9 months from date of corresponding IMEI no. of the unit whichever is earlier
10. Warranty does not cover accessories external to the equipment supplied by the dealer.
11. The Delhi / New Delhi courts shall have the jurisdiction to try any dispute and /or suits related to or arising out of this agreement.

Customer Information Center/ Call Center Number

For any query related to the after sales service and customer support please contact us at the numbers listed below.

	SERVICE
	1800-180-9999*
*MTNL / BSNL **Prefix STD Code	39-01-0909**

BRANCH ADDRESSES

S.No.	Branch	Branch Office Address	STD Code	Phone No.
1	Ahmedabad	LGEIL, 233-234, Platinum Plaza, Judges Bunglow Road, Bodakdev Road, Ahmedabad - 5	079	40040013 / 14
2	Asansol	LGEIL, Block-E, Ist Floor, P C Chattarjee Market, Rambandhu Tala, GT Road (E) Asansol-713303	0341	3292009 / 3292010
3	Aurangabad	LGEIL, 302 CIDCO No 3, Opp Hotel Ramgiri, Jalna Road, Aurangabad - 431003	0240	2474055 / 32095436 / 32095437 / 32095438
4	Bangalore	LGEIL, No. 914, 2nd Floor, Shri Venkateshwara Complex, Opp. IBP Petrol Bunk, 80ft Road, 6th Block, Koramangala - Bangalore - 560095	080	41145145 / 41144750 / 41144751 / 30910754 / 30910753
5	Bhopal	13 A Vignes Warehousing Corporation, Sector-G Govindpura Industrial Area J K Road Bhopal	0755	4062900 / 3092938 / 3959804
6	Bhubaneshwar	LGEIL, Plot No.02, 1st Flr., Bapuji Nagar, Bhubaneshwar-751009	0674	2531430 / 2534280 / 3966525 / 3966526
7	Chandigarh	LGEIL, SCO No. 142-143, 3rd Floor, Sector-34A Chandigarh.-160002	0172	5087389 / 90 / 5089107 / 3256001 / 3256003
8	Chennai	LGEIL, AA11, 2nd Avenue, Fatima Tower, Anna Nagar West, Chennai-600040	044	65510501 ~ 04
9	Cochin	LGEIL, 40/1270, Vasudeva Buildings, T.D.Road, Ernakulam Cochin-682011	0484	2369743 / 2370744 / 2370484 / 4027444 / 4027555
10	Coimbatore	LGEIL, 250a, Sanganur Main Road, Kannappa Nagar, Coimbatore-641027	0422	2332197 / 2332195 / 2332506 / 3094613 / 3094573
11	Dehradun	LGEIL, M - 22, Mobbewala, Tata Commercial Compound, Dehradun Saharanpur Road, Dehradun	0135	2644213 / 283
12	Delhi	LGEIL, A-27, Mohan Co-operative, Industrial Estate, New Delhi	011	26991411 / 12 / 13
13	Ghaziabad	LGEIL, ,J-10, RDC Rajnagar Ghaziabad - 201001	0120	9811354152 / 3 / 64 / 65
14	Goa	LGEIL, Plot No-D-3&D-4, Rego Baug, Alto Santacruz, Bambolim, Goa-403	0832	3294955 / 3294956 / 3294759
15	Gurgaon	LGEIL, II nd Flr, A Block, Centre Point Bldg, Sushant Lok, PH-I, Gurgaon-122001	0124	4047461 / 62 / 63 / 4272867 / 4047460
16	Guwahati	LGEIL, Shantineer Bhawan, C K Aggarwal Path, Chenikurthi, Guwahati-781003	0361	2663895 / 2666958 / 2665983 / 2668984
17	Hubli	LGEIL, 603/1B, Ravi Nagar Road, Behind Renuka Petrol Pump, Gokul Road, Hubli-580030	0836	4250251 / 52 / 2337251 / 52
18	Hyderabad	LGEIL, 1st Floor, Survey No.54, Pulla Reddy Building, Vikarampuri Main Road Kharkhana, Secunderabad - 500004	040	27811732 / 33 / 34
19	Indore	LGEIL, 3rd flr., 304 Bansil Trade Centre, 581/5 M.G.Road, Indore-452003	0731	4065523 / 24 / 40822157
20	Jaipur	LGEIL, B-71, Sahakar Marg, Lal Kothi Scheme, Jaipur-302015	0141	51111118 / 5113028 / 5105392
21	Jalandhar	LGEIL, Village Khajurla, Near Hawali Resturant Jalandhar, Phagwara Highway ,G T Road, Jalandhar	01824	502667 / 508025 / 502668
22	Jammu	LGEIL, Plot No.-52, Yard No. 6, Transport Nagar, Narwal, Jammu-180006	0191	2477420 / 2477419 / 2474396 / 2474384
23	Jodhpur	LGEIL, 22(1-A)/21(2-B)/2, RIICO Heavy Industrial area, Jodhpur - 342003	0291	2742384 / 392
24	Kolkata	LGEIL, 1, Ho-Chi-Min-Sarani, 6th Floor, Metro Towers, Kolkata-700071	033	22883250 / 51 / 52
25	Kundli	LGEIL, Sunshine Enterprises, Sunder Cold Storage, Gt Karnal Road, Kundli-Sonipat	0130	2219201 / 02 / 03
26	Lucknow	LGEIL, B- 537, Hari Kunj, Keshav Nagar, Sitapur Road Lukhnow -226020	0522	2757538 / 39 / 2759121
27	Ludhiana	LGEIL, Village Jhande, Near Badowal Railway Station, Opp ferozpur Road Ludhiana.	0161	2804413 / 19
28	Mumbai	LGEIL, Trade Star, 4th Floor, A Wing, J.B Nagar, Andheri Kurla Road, Andheri (E) Mumbai-400059	022	28352882 - 2887
29	Nagpur	LGEIL, 5a, Road No.13, Behind Mstrc Workshop, MIDC Hinga, Nagpur-440016	07	2
30	Patna	LGEIL, 2nd Floor, Ankita Chandra Deep Complex, Bander Bageecha, Near Samrat Hotel, Patna- 800001.	0612	3299156
31	Pune	LGEIL, 105/106, Premium Point, GM Road, Opp Modern High School, Illrd Floor, Shivaji Marg, Pune -411005	020	66030100 / 732
32	Raipur	LGEIL, Nathani Compound, Shyam Nagar, Katora Talab, Raipur(C.G)	0771	4053171 / 4037470 / 4048745
33	Ranchi	LGEIL, 402, Commerce Tower, Opp. Gel Church Complex, Main Road, Ranchi	0651	3294026 / 2331815 / 3090426
34	Surat	LGEIL, 1001-1004, Ascon Plaza, IInd Flr, Anand Mahal Road, Behind Bhulka Bhavan School, Adajan, Surat-395009	0261	2730982 / 83 / 84
35	Thane	LGEIL, Gall Shop No 6-9, S-2 Golden Park Complex Hardas Nagar LBS Marg Panchpakhadi Thane(West)-400602	022	25472633 / 2637
36	Varanasi	LGEIL, Pama Complex ,DLW, Lahartara Road, Shivdaspur, Manduadih, Varanasi UP-221002	0542	2373432 / 36 / 37
37	Vijaywada	LGEIL, Door No 32-2/1-7, Ratnamamba Street, Prajasakti Nagar, Vijaywada - 520010, Andhra Pradesh	0866	2497283 / 87
38	Warangal	LGEIL, HOUSE NO. 1-8-598/1 FIRST FLOOR, BESIDE HDFC BANK NAKKALGUTTA, HANAMAKONDA-506001 (WARANGAL)	0870	2551453

Dealer name with stamp Dealer address
IMEI No. Date of sale Serial no.....



LG Electronics India Pvt. Ltd., Plot No. 51, Udyog Vihar Surajpur Kasna Road, Greater Noida, U.P.

SERVICE CENTER LIST


LG | CUSTOMER SERVICE

*From: BSNL / MTNL
1800-180-9999*

**From Mobile:
Add local STD Code
39-01-0909**

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Andhra Pradesh	Adhoni	RS CDMA	21/490,Arts & Science College Road, Near Devi Nursing home, Adhoni	9346490905	Mr.Mohan
Andhra Pradesh	Adilabad	KIRAN MOBILE WORLD	7-14-78/A, Near Nethaji Chouk, Cinema Road, Adilabad	9346358181	kiran kumar
Andhra Pradesh	Amalapuram	SANDESH CELLULAR	Shop no 5 R.K. TOWERS COLLEGE ROAD AMALAPURAM	9346398838	Mr.RAVI KUMAR
Andhra Pradesh	Anantpur	RK LG CDMA	Shop No 3, Cellular,Pallavi Towers, Opp to Canara Bank,Subash Road, Ananthpur	9393722777	Sridhar
Andhra Pradesh	Armoor	SAI SRI Electronics	Shop.no:2, mahalakshmi road, Armoor	9392622038	Mr.srinivas
Andhra Pradesh	Bapatla	Vijaya Communications	G.B.C.Road, Bapatla	9346206305	Mr.B.Siva
Andhra Pradesh	Bhimavaram	Gopi Krishna Communications	JP Road Near Mohan Service Center Bhimavaram	9346700202	Mr.Siva
Andhra Pradesh	Chirala	Lakshmi Infocomm	Munthavari street, sangam thestre Road, Chirala	9347052181	Ms.Shakeena
Andhra Pradesh	Chittoor	CMT Computer Services	20-439, A.S.M.STREET, MITTOOR, CHITTOOR	9347361979	Mr.Gopi
Andhra Pradesh	Cuddapah	Srinivasa Communication	Shop No.4, Siddapriya Complex, Opp. HP Petrol Pumping Point, Cuddapah	9346350224	Mr.Sahadeva Reddy
Andhra Pradesh	Dharmavaram	Siddharta Communications	Opp to Sathya Lodge, PRC Circle, Dharmavaram	9347064101	Mr.Naresh
Andhra Pradesh	Eluru	S.S.COMPUTERS	Door.No:23B-4-8/3, Ayyapa Complex, Beside Kanuri Madhavi Hospital, Subbama Devi School Road, R.R.Pet, Eluru	329294	Mr.DIWAKER
Andhra Pradesh	Gudivada	KANAKADURGACOMMUNACTIONS	SHOP NO:4,C/O SURYA RESDENCY, OPP:VIJAYA GAS COMPANY,ELURU ROAD,GUDIVADA	9394220688	Mr.KUMAR
Andhra Pradesh	Gudur	Srinivasa Electronics	Ist floor, Airtel Building, Kummari Veedhi,Gudur	9390829440	S. Naga Suman
Andhra Pradesh	Guntur	Vasavi Associates	Shop No:21,Central Plaza,Naaz Center,Guntur	3257789	MR.Satyam
Andhra Pradesh	Hazurnagar/Kodad	Sri Pavan Electronics	Mallika Towers, Besides Reliance Web World, Kodad	9346901519	Mr Narasimha Rao
Andhra Pradesh	Hindupuram	S.V.A Cellular	Shop.no:3,Vinayaka Lodge, Railway Road, Hindupur	9390000135	Mr. D.B.Ravindra Nath
Andhra Pradesh	Huzurabad	BHARGAVI COMMUNICATIONS	DCMS Complex, Near bus Stand, main road, Huzurabad	9391755619	T.VISHNU VARDHAN
Andhra Pradesh	Hyderabad	SUNBEAM TECHNOLOGIES	120,Chenoy Trade Centre, Parklane, Near Paradise,Secunderabad	40200193 / 66383193	Mr.Suresh
Andhra Pradesh	Hyderabad	Bhagya Communications	Shop no:109, Upper Ground Floor,#12-2-825, S.G.M. Mall, Mehdiapatnam, Hyderabad	32972308, 32001406	Mr.Bipin

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Andhra Pradesh	Hyderabad	JVR Infotech Pvt Ltd	Shop No 8 ,Vanijya Vihar, Nalanda Building, Dilsukh Nagar Main Road, Hydrabad	24161848, 55109604	EV Ramakanth
Andhra Pradesh	Hyderabad	PRIMUS INFOMATIC & SOFTWARE PVT LTD	#18/A,Methodist Complex, 5-9-190, Lane Opp to Chermas, Abids, Hyderabad	66755111	Mr.Govind Kabra
Andhra Pradesh	Hyderabad	Reliable Communication	G-8, 3-6-561, AALTO'S A & M Trade Centre, HIMAYATNAGAR, HYDERABAD	32913251	Mr.Sandeep.soni
Andhra Pradesh	Hyderabad	S V Electronics	Shop No. 41, Nilagiri Block, Aditya Enclave, Ameerpet Main Road, Hydrabad	55754477 32977389	Mr.Pradeep
Andhra Pradesh	Hyderabad	Shweta Communications	Shop No.9, Ground Floor, Pavani Ansuya Complex, Opp. Huda Complex, Tarnaka, Hyderabad	32968162	Mr. Sandeep Heda
Andhra Pradesh	Hyderabad	Shweta Computers	# 1 -7 -69/1 & 2, OPP Aditya Delux Hotel, Near Paradise circel, Sarojini Devi Road, Secunderabad	27721076, -32977548	Mr.Jagdish
Andhra Pradesh	Hyderabad	Sreenivasa Technologies	SAI VIKRAM TOWERS, SHOP NO :4,RELIANCE WEB WORLD BUILDING, Balagi Nagar Kukatpally	32961479	Mr.Praveen
Andhra Pradesh	Hyderabad	Sri Surya Communications	#Madhu Enclave.Street no 06,Shyamal Buildings, Begumpet , Hyderabad	32961127	Mr.Nageswara Rao
Andhra Pradesh	Hyderabad	Sri Varun Electronics	D.No 5-8-344/1, " DHAN BHAGYA ESTATE ", Chirag Ali Lane, Abids, Next to Raghava Ratna Towers, Hyderabad	32900909 55781999	Mr.Alokh Mohan
Andhra Pradesh	Hyderabad	VICTORY ELECTRONICS	Shop No. B-1, Quli Qutub Shah Stadium, Opp. City College, Hyderabad	32408999, 24502339	MR.B.L.VARMA
Andhra Pradesh	Jagityal	SS Communications	Opp to L.G.RAM. Lodge Street, Park Line, Jagityal	9391533535	Mr.Hari
Andhra Pradesh	Jangaon	SKY WIN COMMUNICATIONS	#2-7-134, Beside Bharat Gas, Bus stand Road,Jangoan.	9390102839	VARUN
Andhra Pradesh	Jangareddygudem	SRI DEVI COMMUNICATION	Near Mavullama Temple, Opp.Andhra Bank,Jangareddygudem	227297	Prasanna Lakshmi
Andhra Pradesh	Kakinada	Delta Infotech	Door No.6-1-29, Opp. Swami Vivekananda Park, Jawahar Street, Surya Rao Pet, Kakinada	5593533	Mr. Shivanand
Andhra Pradesh	Kamareddy	Pager King Communication	Sircilla Road, Kamareddy, Dist. Nizamabad	9397366633	Mr. Moizuddin
Andhra Pradesh	Karimnagar	SS Marketers	2-8-40, Mukarampura, Near Circus Grounds, Karimnagar	9391552223	Sujan
Andhra Pradesh	Kavali	Sree Balaji Infotech	Trunk Road,Near Ongole Bus stand, Kavali, Nellore District, Andhra Pradesh	6329567	Mr. G. Sri Sai Charan
Andhra Pradesh	Khammam	Sriven Technologies	D.No:11-2-37,Shop No.3, D.V.Krishna Complex, Beside Baburao Petrol Bunk, Balaji Nagar, Wyra Road, Khammam	325567	Mr.Bhaskar Reddy
Andhra Pradesh	Kothagudam	S.Swathi CDMA Service Center	9-3-3,Above Sindhura Electronics, Near RTC BUS Stand,Kothagudem	9391552228	Mr.niaz Ahmed
Andhra Pradesh	Kuppam	SAGAR COMPUTER SERVICES	14-124, PALACE ROAD, KUPPAM	9391862436	Mr.Sagar
Andhra Pradesh	Kurnool	R K LG CDMA	Shop no:13, First floor, UCON Plaza, Kurnool	220201	Mr.G Rama Krishna
Andhra Pradesh	Machilipatnam	Om Sree Sai Communications	25/276, Kota Vari Tulla Center, Jaganadhapuram, Machilipatnam	9347741777	Mr.Rafee
Andhra Pradesh	Madanapalle	Sri Balaji Computers	Shop No:2, 1st floor, Sri sai Complex, CTM Road, Madanapally	9390025204	Ravi Kumar

Person	State	City	ASC Name	ASC Address	Phone No.	Contact Person
anth	Andhra Pradesh	Mahabubnagar	SRI Chakra mobile care centre	Shop.no:15,Shareef Complex, Near Bus stand, Mahbubnagar	9396348999	Mr.Anil
d Kabra	Andhra Pradesh	Manchiryal	SS CDMA Service Centre	Shop no.7,Mounika Complex,BPL Chourasta,Manchiryal	9394552223	Mr.T. Nagaraju
soni	Medak	Kavali	Balaji Communications	Door.no:1-3-77/j, Opp to State bank of Hyderabad, Main Branch, Main road, Medak	9346439961	Mr. Rajkumar
ep	Andhra Pradesh	Medchal	Khan Electronics	Sanjeeva Reddy Complex, Besides RTC Bus Depot, Medchal	9347222088	Mr. Jaleel Khan
deep	Andhra Pradesh	Miryalguda	Needs Electronics	Jagannath Complex, Opp Bus Stand, Miryalguda	9394645696	Mr Ravi Kumar
h	Andhra Pradesh	Nalgonda	Quintessence Electronics	Shop No :5,Srinivasa complex, Opp to market office,HYD road, Nalgonda	9396610220	Mr Venkateshwar Rao
	Andhra Pradesh	Nandyal	Dhanush Systems,	Dno:25/165 B,Sanjeev Nagar, Near Ramalayam, Nandyal	9392236699	Mr.Ramesh
en	Andhra Pradesh	Narasaraopet	Rajendra Infotech	C/o Hari priya Electronics, Arundelpet, Narsaraopet	224136	Mr.Sasi Bhushan
swara	Andhra Pradesh	Nellore	Siri Enterprises	Co-Operative Bank Complex, 1st Floor, Shop No: 26,Near Gandhi Statue, G.N.T.Road, NELLORE. Andhra Pradesh.	3290339, 9398309571	Mr.Pratap
Mohan	Andhra Pradesh	NELLORE	Balaji Watch & Electronics	16/249,Trunk Road,Nellore	2339999	Mr.Rajesh
ARMA	Andhra Pradesh	Nirmal	OM SAI Electronics	Shop.no:1, Kala Nagar road, Beside 2 town Police station, Nirmal	9390000024	Mr. Mahendar
	Andhra Pradesh	Nizamabad	Satya Electronics	# 7-10-65,Shop no 1 ,1 st Floor,H.M.H.V Complex,Beside Bus Stand,Nizamabad	326000	Mr.Satyam
	Andhra Pradesh	Ongole	TejaSri Communications	37-1-107,Near Mastan Darga Center,Trunk Road,Ongole	9393026115	Mr.SASI BHUSAN
Lakshmi	Andhra Pradesh	Peddapalli (Ramagundam)	Abhi Marketers	Shop No:19/8/291, MRK Plaza, Lakshmi Nagar, Godhavari Khani	9347077009	Srinivas
inand	Andhra Pradesh	Peddapuram	Devi Infotech	Opp.Veternary Hospital, Shop No-1, Santa Market Road,Peddapuram	9394864400	Mr.Siva Kumar
uddin	Andhra Pradesh	Prodattur	SV Techonoligies	4-625-3,Gandhi Road, Opp Karur Vysya Bank, Produttur	9347251806	Mr.Ravi Kumar
	Andhra Pradesh	Puttur	Siva Sai Computer World	8-104/C, VIJAYA LAKSHMI COMPLEX TIRUPATI-CHENNAI ROAD, PUTTUR	9393028024	C.Janardhna Reddy
i Sai	Andhra Pradesh	Rajamundhary	Siri Infotech	Police Welfare Complex, City Hospitals Junction, Danvai Pet Main Road, Rajhamundry	2421567	Mr Raghvendra
ar Reddy	Andhra Pradesh	Raychoti	Raju Computer World	Room No 3 Up Stairs Syeedia complex, bustand road, Rayachoty	9346209881	Mr.Raju
hmed	Andhra Pradesh	Repalle	Sri Satya Solutions	10/14-126,Municipal Office Road,Railpet,Repalle	9396222993	Mr.Sridhar
	Andhra Pradesh	Sangareddy	Sri Technologies	Srimaan Complex, Beside Inspection Bunglow, Main Road, Sangareddy	9391216573	Mr.AJAZ AHMED
	Andhra Pradesh	Sattenapalli	S.S. Communications	Opp.Telephone Exchange, Sattenapalli	9397610550	Mr.Sai
na	Andhra Pradesh	Shad Nagar	Sri Gana Electronics,	Shop No : 2, Khajja Veeresam Complex, College Road, Shadnagar	9392633111	Mr. Vigneswar
	Andhra Pradesh	Siddipet	Gopala Krishana Communications	SHOP NO:13, FIRST FLOOR, MACCA COMPLEX, OPP:CITIZEN'S CLUB, M.G ROAD, SIDDIPET	9392511064	Mr. Kura Giridhar
ar	Andhra Pradesh	Srikakulam	SRI SAI COMPUTER SHOPPE	OPP TEJA TIFFIN CORNER,G. T. ROAD, SRIKAKULAM	9390611779	MR SESHAGIRI
	Andhra Pradesh	Srikalahasti	KSV Computer Services	NNR Buildings, d.no: 16-582, Panagal road, Srikalahasti	9390044399	SAHADEVA REDDY

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Andhra Pradesh	Sullurpet	Sai Baba Electronics,	D.No. 10/47, Bapuji Steet, Sullurpet	9346920527	S. Venkata Krishna
Andhra Pradesh	Tadepalligudem	SRI HARIPRIYA INFOTECH	THOTA GOPI COMPLEX PLOICE QUARTERS LANE, BESIDES ZP HIGH SCHOOL, TADEPALLIGUDAM.	9346408640	Mr.Suresh
Andhra Pradesh	Tanuku	SHIVANAND ENTERPRISES	D/NO-34-3-3, MAIN ROAD GAMINI COMPUND TANUKU.	220489	Mr. SRINIVAS
Andhra Pradesh	Tenali	Vaishnavi Infotech	D.No.22/11/114, Opp.Kanikacharla Kalyanamandapam, Bose Road, Tenali.	9347651330	Mr.Murali
Andhra Pradesh	Tirupathi	CMT Computer Services	18-1-624 VV Mahal Road,OPP HDFC BANK, Tirupathi	3296979	Mr.K Vasu Naidu
Andhra Pradesh	Vijayawada	K L Computer House	39-9-46 SVS Temple Street,Labbipet,Vijaywada	5520461, 5671461	Mr.Kartik
Andhra Pradesh	Vijayawada	V V Communications	28-23-31/32,OPP.SWARUGHA FOODS,VIJAY TALKIES CENTER,VIJAYAWADA	9396467789	Mr.Rahul
Andhra Pradesh	VIJAYAWADA	Balaji Watch & Mobiles Pvt.Ltd	29-37-79, Eluru Road, Opp. Vijaya Talkies, Vijayawada	6648888	Mr.Prasad
Andhra Pradesh	Vishakapatnam	Sri Sai Ganesh Infotech	G5,Ground Floor, Backside of Sangam-Sarat Theatre,1st Lane,Dwarka Nagar, Visakhapatnam	3258777	Mr.Chandra Shekar
Andhra Pradesh	Vishakapatnam	Jai Bharani Communications	Door No:52-11-7/7, Sapthagiri Plaza, Old Resuvanipallem, Vishakapatnam-13	3242111	Mr. P.Venkatapathi Raju
Andhra Pradesh	Vizayanagaram	S R TECHNOLOGIES	DRNO 17-2-29, RAJABAZAR, VIZAINAGARAM	9346418791	Mr.Balakrishna
Andhra Pradesh	Vuyyuru	Sugreeva Communications	Behind Datta Automobiles, Katturu Road, Vuyyuru	9393033355	Mr.Phani
Andhra Pradesh	Wanaparthy	Sri Ganesh Electronics	Shop No : 16-63, Opp R R Compey, Wanaparthy	9396800275	Mr Deva Raj
Andhra Pradesh	Warrangal	S S Marketers	6-1-73/1, Sai Bhavan, Sridevi Theatre Road, Hanamkonda, Warrangal	2552223	Mr. L.Srinivas Rao
Assam	Guwhati	A B PERIPHERALS & SERVICES	Wahed house, 2nd Floor,Opp ASTC Volvo point, Ulubari, Kamrup, Guwahati	2732417	Wassi Ahmed
Bihar	Arrah	Surya Services	Sushila Bhawan, Suryapuri colony, By pass road, Arrah	9334538845	Sanjay Kumar
Bihar	Aurangabad	Computer Sansar	L.P.Complex,old G.T.Road, Aurangabad, Bihar, PIN:824101	9334926768	Shreeniwas
Bihar	Begusarai	Krishna Communication	Eashwari Complex,Dak Bangla Chowk, Bishnupur, Begusarai, Bihar-851101.	9334341700	Dinkar Kumar
Bihar	Bhagalpur	S.K. Communication	NEAR RAILWAY STATION,Super market complex, Patel Babu road, BHAGALPUR -812001	9334255275	Kundan Kumar
Bihar	Bhagalpur	Printronic Infosolutions	Ganpati Complex,1st floor, Patel babu road	9934629247	Himansu Shekhar
Bihar	Biharsharif	Shanya Infotech	Magdha Commecrcial Complex, 1st.Floor, Shop.No.5, MG Road, Bharaopar,Bihar Sharif, Nalanda Dist. Bihar,Pin:803101	9334048037	Amit Kanchan
Bihar	Chapra	Ambey Associates	D-23, Hathwa Market, Chapra,Dist: Saran, Bihar, Pin:841301	9334295605	Jayant Kumar
Bihar	Darbanga	Prime Computer	Hanuman Nagar, Doner Road, Darbanga.	2220560	Abhinav Kumar Verma
Bihar	Gaya	Agrawal Distributors	Swarajpuri Road (Opp. Nagbatia Road), Waves Building,Gaya, Pin:	9334218122	Lalit Agrawal
Bihar	Muzafarpur	Krish Enterprises	Nr.Kanhoulinaka.no.2, Kachisarai Road, Muzafarpur.	9304410745	Sanjeev Kumar

Person
a Krishna
h
IVAS
i
u Naidu
d
ra Shekar
katapathi
rishna
Raj
nivas Rao
imed
umar
as
umar
Kumar
Shekhar
chan
umar
Kumar
awal
Kumar

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Bihar	Patna	INFOTEK TRADING COMPANY	1st floor, City Palace, New Dak Bunglow Road, Patna-800001	2227166	Sanjay Choubey
Bihar	Patna	Synerzy Trading Company	G-01,Chanakya Plaza Complex,Main Road, Kankarabagh, Patna.8000020	2356900	Vikas Chandra
Bihar	Patna	COMPETENT MOBILE SERVICE	Shop 1, Hotel Lalitha Complex, East Bowring Canal Road, Patna	9334027706	Mohit Ahluwalia
Bihar	Patna	Micro Zone-Patna	17/C,S,K Puri, Near Basawan Park	3294696	Mithlesh Kumar
Bihar	Purnea	Micro Zone-Purnea	Narottam Hata,NH-31, Purnea	9304166633	Amit Kumar
Bihar	Sasaram	Nandika Enterprises	Hari Complex, Panjab National Bank, Sasaram, Rohtas (Bihar)	4222008	Abhinav Gupta
Chhattisgarh	AMBIKAPUR	NEHA COMMUNICATION	Ramanuj Ganj road, Opp. Kosa Form , Ambikapur , Sarguja, Pin-497001	440414	Mr.Rishi Dubey
Chhattisgarh	Bhilai	A B Automation	Shop No 117 , Ground Floor , Chouhan Estate, Supela Bhilai	09329750711/ 0788-2295989	Mr. Satish Singh
Chhattisgarh	Bhilai	Sai Ram Electronics	SHOP-NO-52/90, HIMALAY COMPLEX, AKASH GANGA, SUPELA, BHILAI	4038917	Mr. Balan
Chhattisgarh	Bilaspur	Mahamaya Infotech	Shop No 203, Jain Plaza, Ground floor, Link Road, Bilaspur	2413865	Mr. Pawan Kumar
Chhattisgarh	KORBA	STAR MOBILE SERVICES	SS Plaza FD-13 PH Road Korba Chhattisgarh	9300401485	Mr. Anish Menon
Chhattisgarh	Raigarh	BLUE CHIP COMPUTER	Purana Sadar Bazaar, Raigarh, Chhattisgarh.	329888	Mr. Ashok Agrawal
Chhattisgarh	Raipur	Cybernet Systems	B-2,1st Floor, Garchaz Complex, Jail Road, Raipur - 492001	077-14069971	Mr Anand Singh
Chhattisgarh	Rajnandgaon	BHAVYE SERVICES	SHOP NO 5 , BELOW SBI , KAMPTEE LINE , RAJNANDGAON	395200	MANISH GOLCHA
Delhi	Delhi	Aegiss Infotech	UG-25 , Ansal Chamber -2, 6, Bhikaji Cama Place, New Delhi-110066	65477740 , 9312294105, 9313796774	Mr. Atul Gupta
Delhi	Delhi	Arham Infotech Services	1/1, Regal Building, Near Malik Sweets, Connaught Place New Delhi - 110 001.	011-41501124, 011-32584421	Mr. Anil Surana
Delhi	Delhi	Comhard Systems	D-30,31, First floor, Near Hotel Shipra, Main Vikas Marg, Lakshmi Nagar	011-32955887, 9818867678, 011-32979819	Mr Ravi Kant Gupta
Delhi	Delhi	Comhard Systems	B-120, Hardev Puri, 100 Feet Main Road, Near MTNL Office, Nathu Colony Chowk, Shahdra, New Delhi - 110 093.	011-32575507 , 011-32572427	Mr. Ravi Kant Gupta
Delhi	Delhi	Connexions and Communications	183, Avtar Enclave, Opposite Nirula's , Pashchim vihar ,New Delhi-110063	011-32451431, 011-65237374	Mr. Bhupinder Agrawal
Delhi	Delhi	Cube Engineers and Consultants Pvt Ltd	A-65, Naraina Industrial Area, Phase-1, New Delhi	09312224103, 011-65450272, 41411623	Mr. Arvinder
Delhi	Delhi	Innovative Telecom	304 , GDITL Northex Towers, A-09 ,3rd Floor , Northex Tower, Netaji Subhash Place, Pitampura, New Delhi-110 088.	011-32925753, 011-65154343, 9811682453	Mr Manoj Garg
Delhi	Delhi	Nice Telecom	15/19 & 15/21, DDA Complex, Nangal raya, Near D Block, Janakpuri, Delhi - 110046	011-32607072, 0-9213264403	Ripul Garg

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Delhi	Delhi	R K Communications	2516 Hudson Lines, Kingsway Camp-Nr. Kamla Nagar, New Delhi	011-32508861, 9312606463	Mr. Pradeep Aggarwal
Delhi	Delhi	Sagar Technologies	J-39,Central Mkt, Lajpat Nagar-II, New Delhi-110024	011- 65425644, 9350224692	Mr.Manoj Kumar
Delhi	Delhi	Sukriti Communication	101 Patparganj- Mayur Vihar phase -1 - New Delhi -110091	011-32498011, 011-65238011	Mr.Dipendra kumar chaturvedi
Delhi	Delhi	Touch Tone Telecom	B-52, First Floor, Kalkaji, New Delhi	011 32939031, 011-65672800	Ashish Dey
Delhi	Delhi	Ucom Technologies Pvt Ltd.	45, 1st Flr, Corner Mrkt, Malviya Nagar, New Delhi - 110017	011-41745469, 09212131300	Mr. Neeraj
Delhi	Delhi	Telecom systems	67/4, harshvihar chowk, pitampura, new delhi	9910089333	mr. Satbir
Delhi	Delhi	Shine telecom	N-18, SOUTH EX-1, NEW DELHI	9811143204	Mr. Naveen Goyal
Delhi	Delhi	Elcom Trading Company Pvt. Ltd.	G-1, Goverdhan Building, 53-54. Nehru Place, New Delhi -110019.	9310577009, 011-64582709	Mr. Somesh Narang
Delhi	Delhi	Teletalk	C-21,First Floor, Near Bus Stand, Bhajan pura, Delhi-11053	9818400551	Mr.B.c. Vashist
Goa	Panjim	Mandovi Mobiles	Mohidin Towers Do. No. AS3 Opp to Hotel Manashanti Dadavaidya rd Panjim-403001	6452949	Prakash
Gujarat	Ahmedabad	Vision Communication	33, 1st Floor, Sukh Sagar Complex, Opp. Dinesh Chamber, Bapunagar, Ahmedabad	65122322	Mr Ajay Kachhadiya
Gujarat	Ahmedabad	M Age Cellnet	A-176, Popular Plaza, Near Someshwar Part -1, 132 Ft. Ring Road, Satellite, Ahmedabad	30122838	Mr K Jairaj
Gujarat	Ahmedabad	A Com Technologies	Shop No-37, 1st Floor, Shubh Complex, Near Rajasthan Hospital, Camp Road, Shahibaug, Ahmedabad	32940560	Mr. Vijay.S.Gohel
Gujarat	Ahmedabad	Mishree Communication	FF-17, RUDRA SQUARE, OPP. JUDGES BUNGALOW, POLICE STATION, BODAKDEV, AHMEDABAD	32508491	Mr. Mitesh Patel
Gujarat	Ahmedabad	Silicon Valley	9, Gokul Palace, Maninagar Cross Road, Maninagar Ahmedabad	30225430	Mr. Rajesh Patel
Gujarat	Ahmedabad	Shiv Sai Communications	21,Municipal Market, C.G.Road, Ahmedabad	66057999	Mr. K.Jayraj
Gujarat	Amreli	Precision Telecom	32,33 Opera House, Station Road, Amreli.	230940	Mr. Kamlesh Tank
Gujarat	Anand	Desktop Infosystems	B/10, Vaibhav Tower, V V Nagar Road, Anand	246885	Mr. Dipesh Patel
Gujarat	Ankaleshwar	Akshar Telecom	C 1 Keval Shopping Center,old National Highway No.8,GIDC ,Ankaleshwar	02646-250860	Mrs. Anita Amin
Gujarat	Bharuch	Akshar Telecom	Pramukh Swami Complex, Panch Batti, Bharuch	26422241027	Mr. Hanif Patel
Gujarat	Bhavnagar	Shivshruti Services	98/B, Makvana Building, Down Chowk, Bhavnagar	3296222	Mr.P D Jala
Gujarat	Bhuj	Infotech Computer	2nd Floor, NarNarayan Chambers, Opp Indian Airlines Office, Station Road,Bhuj	324295	Mr. Vasant Mepani
Gujarat	Gandhidham	Vansh Electronics	Shop No. 35, Swami Vivekanand Complex, Near Oslo Circle, Gandhidham	232739	Mr. Siddarth Cajjar
Gujarat	Gandhinagar	Creative Communications	Shop No 102,Suman City,Sector 11,Gandhinagar	23226241	Mr. K.J.Barot

Person
Deep
Aj Kumar
Ra kumar
EY
Aj
R
An Goyal
Ash
/ashist
Ya
Aj
S.Gohel
Sh Patel
Sh Patel
Raj
esh Tank
h Patel
a Amin
f Patel
ila
nt
arth
arot

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Gujarat	Godhra	Binary Computers	34, Lokhandwala Complex, LIC Road, Nr. Chitra Cinema, Godhra.	9376589019	MR. A. Raja
Gujarat	Himmatnagar	Jay Telecommunications	B-F 105, 1st floor, Durga Complex, Near Railway Station, Himmatnagar	329532	Mr. Manibhai Patel
Gujarat	Idar	Maruti Communication	3, Sarvoday Market, Near Bus Stand, Behind Sarvoday Guest House, Idar		Mr. Niraj Patel
Gujarat	Jamnagar	Sudarshan Infosys	"Shraddha", Park Colony, Motor House, Near UTI Bank, P.N.Marg, Jamnagar	2552696	Mr. Amit Unadkat
Gujarat	Junagadh	K.J.Traders	29/30, Danapith, Junagadh	2627320	Mr. Paresh Rughani
Gujarat	Kalol	Maitree Communication	B/93,Yogi Complex, near Mahendra Mill Road,Kalol	325288	Mr. Jignesh Shah
Gujarat	Mehsana	Prime Computer Consumables	83-B, Vimal Super Market, B K Road, S.T.Workshop Road, Mehsana	2325123	Mr. Suketu Patel
Gujarat	Morvi	Pulse Sales and Services	Madhav Market, 1st Floor, Near New ST Stand, Sanala Road Morbi.	300433	Mr. Natubhai Patel
Gujarat	Nadiad	D.C. Infosystems	105, Municipal Shopping Centre, Opp.Paras Cinema, Santram Road, Nadiad.		Mr. Dipesh Patel
Gujarat	Navsari	Deep Enterprise	10, Upper Level, Diamond Palace, Sattabir, Sayagi Road, Navsari-	02637 324095	Mr. Vinod Kasundra
Gujarat	Palanpur	Shree Manibhadra Mobile	16, 1st Floor, Aroma Arcad, Opp. Joravar Palace, Palanpur	320321	Mr. Panchal Sunil D
Gujarat	Patan	Able infotech	F/9, palika bazar complex, rajmahal road,near sanktoba hall, Patan	226400	Mr. Rakesh Bhai
Gujarat	Porbandar	Varun Infotech	1ST Floor,Garden Cafe Building, Opp.New Fountain, Nr.R.T.O Office, Porbandar	3290285	Mr. Mitesh Changela
Gujarat	Rajkot	Joshi Telecom	Shop No.8, Kuber Complex, Opp Chandubhai Bhelwala, Dr Yagnik Road, Rajkot	6530707	Mr Jiten Dave
Gujarat	Rajkot	Roopang infocare	Vinod Nivas, 4, Sardarnagar(West), Nr Astron Cinema, Rajkot	6950111	Mr. Kishore Patel
Gujarat	Sanand	Ravi Communication	37,Sagar Complex, Opp.Hotel Khiabar, Sarkhej Bavla Cross Road, Sanand	32401211	Mr. Ravi N
Gujarat	Surat	Om Sai Services	39,Golden Point,Near Science Laboratory, Ring Road, Surat -	2613231233	Mr. Dharmesh Patel
Gujarat	Surat	Yash Telecom	M-20, Centre point, Near Kadiwala High School, Civil Cross Road, Ring Road,Surat-395002	0261 2477903	Mr. Rehan Saikh
Gujarat	Surat	Excel Solutions	H-3, Ruchi Flats, Near Iqara Building, Adajan Hazira Road. Surat-	0261-6544500	Mr. Virender Jain
Gujarat	Surendranagar	Nihaal Computer Services	94, old housing board, opp school no 13, Surendranagar	320375	Mr. Sikandar
Gujarat	Vadodara	Shreeji Telecom	Gf 13, Sterling Shopping Center,R.C.Dutt Road,Alkapuri, Vadodara -	0265-3059363	Mr. Jignesh Gohel
Gujarat	Valasad	Klassik Stationo Products	10, Jethalal Mulji Market, Halar Road,Valsad -	02632-329363	Mr. Darshan Panchal
Gujarat	Vapi	Klassik Stationo Products	116, Bhanudarshan Co-Op Society, Koparli Road, Near Gunjan Cinema, GIDC, Vapi	0260-3292363	Mr. Avishek Suhasaria
Haryana	Ambala	Bee Ess Aar Communication	92-93, Gandhi market, Ambala Cantt-133001	2641234,	Rajiv Gupta

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Haryana	Bahadurgarh	Unique Telecom	5,Rajaram Market, Main Najafgarh Road, Bahadurgarh, Near Bajaj Showroom	9315873676, 9350941877	Mr. Harinder
Haryana	Bhiwani	Sandeep Electronics	10 th Plot, First Floor, Circular road, Mahem Gate Chowk, Near Dr. Kajal's Nursing Home, Adjacent to Rameshwar's Sweet House, Bhiwani, Haryana - 127021	252000	Mr. Sukhveer Saini
Haryana	Faridabad	Comsoft Computers	601/1 Gopi Colony Chowk- Sector-19 , Near Prem Prakash Ashram, OLD Faridabad-121002	0129-3293512, 0129-4104252, 9310977888	Mr. Ashwani Jindal
Haryana	Faridabad	VR Infocomm	Shop No.44, Neelam Fly Over, Neelam Chowk, NIT Faridabad.	0129-4031959, 0129-3208737	Mr. Vinod Kumar Gupta.
Haryana	Faridabad	Sky lark mobile point	4, G.T.Road, Near Bus Stand, Marla Colony, Fatehabad	0989655244	Pankaj
Haryana	Gurgaon	Signature Communications	B-100 A , South City -1, Opposite - Huda Gymkhana Club - Gurgaon 122001	0124-3256565, 0124-4102709	Raj Kumar Garg
Haryana	Gurgaon	Lalji Communication	SCO-31, - First Floor, Above MTNL Sanchar Haat, Main Market, Opp. BSNL Exchange, Sector-12A, OLD Gurgaon -122001.	95124- 3200900	Mr.Bharat Bhushan
Haryana	HISAR	M K ELECTRONICS	SHOP NO-4A,FIRST FLOOR, NEELKANTH COMPLEX, CAMP CHOWK, MAIN DELHI RD.	9991090260	MANMOHAN KRISHAN
Haryana	Hissar	Parnami Communication	32,Neel Kamal Complex, Red sqaure Market,Near Elite Cinema Hall, Hissar, Haryana-125001	09354332000	Mr. Pradeep Garg
Haryana	Jind	Gaurav Telecom	Main Bazar, Near rani Talab, Near Bharat Electronics, Jind	325400	Deepak Garg
Haryana	Kaithal	Mahesh Communication	Shop no.22, Bajrang Bali Market, Near Randhir cinema- Kaithal	9315146000	Mr. Mahesh
Haryana	Karnal	Mass Communication	Shop No.69, Main Market, Ground Floor, Moughal Canal, Karnal - 132001	3290717	Mr.Harish
Haryana	Kurukshetra	Bharti Communication	3,Krishna Market, Opp.Abhay Palace, Pipli Road,Kurukshetra,Haryana-	01744-327717	Mr. Ramesh
Haryana	NARNAUL	PRIME COMMUNICATION	Shop no.8 , 1st Floor Taneja complex, near Nirula Hotel , main Road Narnaul	9355375351	MR. Naveen
Haryana	Palwal	Shree Ganesh Communications	Basant Apts, Shop No.5, Kithwari Chowk, Mathura Road, Near Saraswathi School, Palwal	01275-321028, 09315403328	Harish Chandra
Haryana	Panipat	INS Telecom	2, Bishan Sarup Colony, Opp Bus Stand, Near Hotel Deep, Panipat	3291860	Jagdeep Sachdeva
Haryana	Rewari	Mahak tele services	53-A, Model Town, Near Shreeji restaurent, Rewari	01274-329222	Gaurave yadve
Haryana	Rohtak	Telecentre	Shakti Market, Civil Hospital Road, Near Chhotu Ram Chowk, Rohtak-124001	247242	Mr.Madaan
Haryana	Sirsa	Sirsa Communication	1 68,Huda Complex, Old Bus Stand, Sirsa	0166-329591	Rajindera
Haryana	Sonipat	Teleworld	Shop No 20, 1st Floor, M.C.Market, Subhash Chowk, Sonipat, Haryana-138001	3290889	Vipin Dua
Haryana	SONIPAT	RELIABLE TELLY SHOPPE	OPP. OLD CIVIL HOSPITAL RLY ROAD SONIPAT NEAR S.B.I. BANK, SONEPAT	9991090252	UMESH CHAUDHARY
Haryana	YAMUNAGAR	KRISHNA COMMUNICATION	SHOP NO.19, 20-A 1ST FLOOR, WORKSHOP ROAD, YAMUNAGAR	9354784019	MR. SURESH/ Mr.Sandeep

Person
nder
veer
vani
d Kumar
ar Garg
it
IHAN
ep Garg
Garg
esh
h
esh
een
handra
a
yadve
an
a
a
HARY
ESH/
eep

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Haryana	Yamunanagar	Manish Communications	Shop No.3, Sharma Colony, Near Mahindra Petrol Pump, Yamunanagar - 135005	233277	Vinod Kumar Mittal
Himachal Pradesh	MANDI	V.M. COMMUNICATION	NEAR PNB MOTI BAZAAR, MANDI-175001	9816024978	M Mahender Singh Thakur
Himachal Pradesh	Palampur	Electronic Home	Kallu Di Hatti,PO Maranda Thasil, Palampur, Distt-Kangra-176102	01894238463	Mr. Ravi Kumar
Himachal Pradesh	Poanta Sahib	SINGAL MARKETING	Badri Nagar,Near LIC Office, Poanta Sahib	9318715848	Mr. Rajesh singal
Himachal Pradesh	Shimla	Hanu Computers	76/ 9, 2nd floor LoweR Bazar Shimla	9418068421	Sandeep Patial
Himachal Pradesh	Solan	Vikas Mobile Repair Center	MOHAN COMPLEX, First Floor Upper Bazar, Solan-173212	9816271183	Vikas
Jammu	Jammu	MOBILE CARE	608-A Gandhi Nagar Behind Laxmi Narayan Mandir	0191-2436814	Mr Dixit Gupta
Jammu	Srinagar	THE NET SURFER	2nd Floor Mohi-ud-Din Building, Poloview, srinagar	0194-2459549	Mr Wasim
Jammu	Udhampur	SERVICE SOLUTIONS	Ward No. 15 Shakti Nagar Opp. Old ITI Udhampur	01992-276724	Mr Rakesh
JHARKHAND	BOKARO	Digital Equipment Centre	GB-11, City Palace, Opp.Indian Bank, Bokaro.	9334072270	Dewashish Ojha
Jharkhand	Daltonganj	MAA MOBILES	Jail Road, Jail Hata, Dalton Ganj-822101	9304285663	Mr.Navin Kr. Kashyap
Jharkhand	Deogarh	Kanan Electronics	Hotel Relax Complex, BLC Road, Deogarh-814112	9304059528	Mr. Mahesh Sharma
Jharkhand	Dhanbad	Nirmala Entreprises	Ground Floor, Muskan Complex, Nr.Subhash Chowk, Dhanbad.	9334027583	Mr.Niraj Sinha
Jharkhand	Godda	Karan Mobilink	Maa Kalyani, Katra, Main Market, Godda-814133	9334525200	Mr.Saroj Kumar Jha
Jharkhand	Hazaribagh	Digital Services	Plaza Mkt, pugmill road, Nr.Kallu Chowk, Hazaribagh.	9334599570	Mr.Shish Alam
Jharkhand	Jamshedpur	Tirupati Teletech	Chakravarti Compound, Near Hotel Castel, Contractors area, Bistupur, Jamshedpur-831001	0657 3293331	Abhijeet Mukherjee
Jharkhand	Jamshedpur	Prasad Electronics	Nr.Bus stand,Community Center, Kagal Nagar, Jamshedpur.	0657-2226077	Mr.Raju/ Saritha
Jharkhand	Ramgarh	Shreyas Empaire	Bus Stand Complex, Ramgarh-829122	9334085642	Mr.Piyush
Jharkhand	Ranchi	Balaji Infotech	Near Dr.Kashyap Eyeclinic, Purulia Road,Ranchi.	0651-3205400, 9304412277	Mr. Sanjeev, Mr. Sunil Kedia
Jharkhand	Ranchi	Satya Systems & Solutions	158, Opp Hotel Palace, Kadru, Ranchi-834002	0651 3291019	Amit Rastogi
Karnataka	Anekal	Sri Venkateshwara Communications	# 37, KSRTC COLONY, HOSUR MAIN ROAD,ANEKAL TALUK, BANGALORE - 562106	320078	R.Jaganath
Karnataka	Bagalkote	Turning Point Computers	Opp. VRL Booking point, near Engg college BEC road, Vidyagiri, Bagalkote	329310	B.M. Hiremath/ Veeresh
Karnataka	Bailhongal	3G Communication	Shop No 459\2 Near Inchal Cross Belgaum Road Bailhongal-591102	9343815097	Vishwanath
Karnataka	Bangalore	Ascent Communication	No:113, St Johns Church road, Bangalore - 560005	32914856	Kumaresan
Karnataka	Bangalore	Insta Service Point	NO:64,Mission road, SATHI COMPLEX, BANGALORE-27	22107560	Venkatesh
Karnataka	Bangalore	Optima Mobile Services	24/2,Dr.Rajkumar Road, Near Subramanyanagar Police Station, 2nd Block, Rajajinagar, Bangalore - 560 010	23131953	Unni Krishnan

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Karnataka	Bangalore	Optima Mobile Services	P-3, Mallikarjuna Complex, Opp R T Nagar Police Station, 80 Feet Road, R T Nagar, Bangalore-560032	32710202	Madan
Karnataka	Bangalore	Pranav infocom	No 102, Surya Mansion, 7th Main, 4th Block, JAYANAGAR, BANGALORE -560011	9343023209	S.V.Sirish
Karnataka	Belgaum	Hello India Telecom	G-4,Maratha Mandir Complex, Khanapur Road, Near Railway Flyover, Belgaum - 590 001.	2420533	Mohan
Karnataka	Bellary	Shri Vinayak Electronics	# C1, R K Complex, KC Road Bellary-583103	655043	Devandra / Richard
Karnataka	Bhadravati	Digital communication	SR Complex 4th cross B H Road Bhadravathi-577301	9341081291	Nagabushan
Karnataka	Bhatkal	Vijay Communication	Hussian Complex Bunder road Bhatkal - 581320	329327	Vittal H.Naik
Karnataka	Bidar	Mayuri Infotech	Ravi complex,shop no: 4,Udgir road,Bidar-585401	225544	Ravi Halhalli
Karnataka	Bijapur	Turning point computers	Khed building,opp Vijaya college, Sholapur road, Bijapur-586103	329318	S.M.Hiremath
Karnataka	Channapatna	C&C Technology	"Ramanujam Nilaya" No.2104, 11th Cross, Kuvempunagar B M Road, Channapatna - 571501	324222	Charan
Karnataka	Chikaballpur	Sri Ram Prasad Enterprises	Post office road Chikaballapur-562101	329579	Vardharaj / Ram prasad
Karnataka	Chikmaglaur	Cell Tec Electronics	ragavendra complex, NMC circle,Neharu road, Chikmaglur - 577101	9341013183	Prem kumar
Karnataka	Chintamani	Amrutha Mobiles	Cajanna Circle Chintamani - 563125	9342262811	Sudarshan Reddy
Karnataka	Davangere	Kruthika Communication	Shop No: 6, Park View Plaza, (Income Tax Office's Ground Floor) , 4th Main, Near Vishweshwaraiah Park, P.J. Extension, Davangere-577002	395444	Sujay
Karnataka	Doddaballpur	Santosh Communication	VITOBHA TEMPLE ROAD, OPP ASHWINI HOSPITAL, DODDABALLAPUR -561203.	9341736645	Santosh
Karnataka	Gadag	Tranquil Telecom Service Pvt Ltd	Shop No12, Siddalingeshwar Complex Below SBM, Station Road,Gadag District Gadag-528101	576998	Raju / Zakir
Karnataka	Gokak	Cell World	Basaweshwara circle opp-court Gokak - 591307	93438-73777	Shivanand / Chougala
Karnataka	Gulbarga	Aishwaraya Communication	C-9, Asian Plaza S.V.P.Chowk Main road Gulbarga-585102	329447	Mallikarjun
Karnataka	Hassan	Sree Digital Solutions	1380 Mission Hospital road opp Hindibed college - 573201	329481	Vidya Shankar
Karnataka	Hosakote	Emposys Communication	Shop no 1, Mahalatha Devi Complex M V Badavane, College Road Hoskote-562114	652532	Raghunandan
Karnataka	Hubli	Shruti Services	shop no : B6, Laxmi complex, Court circle , Hubli- 580020	3290671	Mahendar
Karnataka	Hunsur	Sriram Infocom	No.6, Municpal complex, H.D.Kote road circle - 571105	253699	H.H.Pradeep
Karnataka	Kadur	Ashwa Tele Mobiles	TB Road Kadur -577548	9341033310	R.Ananda Murthy
Karnataka	Kankapura	Sumukh Communications	Harshitha Complex, Budikere, Bangalore main rd, Near KSTC Bus stand Kanakapura-562117	9342743344	R.C.Harish
Karnataka	Karwar	Mithun Tele Solution	Prema complex Civil court road opp SBM Karwar -581301	9341199222	Mithun palyunker
Karnataka	KGF	Global Net Communcations	Opp. King George Hall, Geetha road Robetson pet, KGF - 563122	329559	Shiva Kumar

Person
a /
han
Naik
talli
math
/ Ram
nar
in Reddy
skir
d /
a
jn
ankar
ndan
ir
ep
a Murthy
sh
alyunker
mar

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Karnataka	Kolar	Seanmatrix	No:384,Suguna comples, Near KSRTC bus stand, Anthargange road, Kolar 560101	2228714	Shetty
Karnataka	Kumta	Krishna Mobiles	938, College road, NH 17, opp RWW, Kumta - 581343	329607	D.V.Prabhu
Karnataka	Kundapur	Reya Mobiles	Vaishali complex I flr Shastri circle, Kundapur - 576201	320866	Anantha / Ramya
Karnataka	Madikeri	C.M. Communications	Shop no. 8, M A Complex 1st flr Kohinoor rd Madikeri	9343837555	Mohamad Sharief
Karnataka	Mandya	C & C Technology	2068, First Cross, Krishna Krupa Nilaya Subhash Nagar, Mandya-571401	320777	Charan
Karnataka	Mangalore	Innovative Infocom	15-10-537/11, Jayavarma Centre, Mallikatte Circle, Kadri, Mangalore - 575002.	6563244	Sebastian Fernandes
Karnataka	Moodabidri	Media Guard Technologies	Rajeev Gandhi complex main road Moodabidri	325909	Vishwas Kumar
Karnataka	Mysore	K.K.Marketing	1432/9, Tribhuvan Towers, opp Veterinary Hospital, Dewan's Road, Dhanwantri Road Cross, Mysore -570001	4258613	Karunakaran.
Karnataka	Nipani	Manusoft Computers	Dumale Complex Chikodi road Nipani - 591237	9448148005	Mahesh Dumale
Karnataka	Raichur	Akshay Electronics	1st floor, hotel UMA complex, station road, Raichur - 584101	329673	Narasimhlu
Karnataka	Ranibenur	Kruthika Communication	LIC Building Opp to Gupta Petrol bunk PB road Ranebennur-581115	231444	Sujay
Karnataka	Shimoga	Chetan Electronics	C-5, Kenchappa complex, Durgigudi main road, Shimoga-577201	9343370193	Panduranga rao / Binoy
Karnataka	Tiptur	Shree Digital Solutions	Nanjappa complex, opp city union bank, BH road, Tiptur - 572201	9343813731	Vidyashankar
Karnataka	Tumkur	Durga Communication	No.14 CMI Complex, opp Jayadeva Hostel, B.H.Road - 572101	2256184	Naveen Kumar
Karnataka	Udupi	Sanman Mobile Services	Shop No: 15, Simaz complex, Diana circule, Court road, Udupi- 576101.	3955770	Prakash
Kerala	Alappuzha	GETRONICS	FIRST FLOOR, KARTHIKA BUILDING, OPP SDV BOYS HIGH SCHOOL, COURT ROAD, ALLEPPY.	3290446	OMPRAKASH
Kerala	Alathur	MARSTEK	12/950, Ground Floor, AR Complex, Opp. Munsiff's Court, Alathur, Palakkad Dt.- 678 541	04922-321311	Mr. Rajesh. V.
Kerala	Aluva	SED INFOSYS	BUILDING NO 12/57 DOOR NO 8, FIRST FLOOR, POOTHULLIL BUILDING, ALUVA - 683 101.	3235599	Sudheesh
Kerala	Attingal	AM Technologies	Mamam, Near Dreams Theater, Attingal	3290301	Saji
Kerala	Badagara	Amarkish Communications	1st Floor, Sarala Complex, Near KVR Motors, N.H. Bypass Road, Nut Street, Vadakara-673101.	0496 - 3255756	Mr.Jeeju / Mr. Baiju
Kerala	Cherthala	Cherukattu Phones	Krishna Building, Opp govt boys high school, AC road, Cherthala	9388441434	Mahesh C D
Kerala	Ernakulam	TELETECH SYSTEMS	20, First Floor, Penta Estate, above Airtel office, Janatha Junction, Palarivattom, Cochin-25	3207554	SONY THOMAS
Kerala	Ernakulam	Zenicon Infocom(P) limited	Above Syndicate Bank, Opp Cochin Shipyard, M.G.Road, Cochin-15	2359511	Jaimon Joseph
Kerala	Ernakulam	Guidelines	Ground Floor, Mundukottackal Estates, Kadavanthara, S A Road, Cochin	4000113	Manoj G
Kerala	IRINJALAKKUDA	NICE MOBILES	NICE BUILDING, ST. JOSEPH'S COLLEGE JUNCTION, IRINJALAKKUDA - 680121	0480-3291515	MR. SEBASTIAN

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Kerala	Kalpetta	Mobi Care	Apasara Building, Near Municipality Office, Main Road, Kalpetta	04936-329366	Thanseer
Kerala	Kanhangad	Xn COMPUTERS & DATA CARE	BENGACHERY COMPLEX, OPP.VYAPARA BHAVAN, T B ROAD JN, KANHANGAD.	0467-3259755	Mr.SANDEEP
Kerala	KANNUR	SAHAR COMMUNICATIONS	SB-666-C & D, PRESTIGE CENTRE, GROUND FLOOR, SUB REGISTER OFFICE ROAD, KANNUR.	0497-3258585	AJAI ABHIRAM
Kerala	Karunagapally	Supreme Enterprises	Valiyath Plaza, Opp to KSRTC Bus stand,Karunagapally	2620282	Mr. Ratish/Prem
Kerala	Kasargode	Xn COMPUTERS & DATA CARE	BENDICHAL COMMERCIAL COMPLEX, PRESS CLUB JN, MG ROAD, KASARGOD.	04994-324755	Mr. SANDEEP
Kerala	Kollam	Digital Infosystems	MC-3087, New Block, Bishop Jeromi Nagar, Chinnakada, Kollem-691001	2760647	Johnson Lawrence
Kerala	Kottarakkara	Sivashakthi Communications	KP II/1574, Valiyavila bldg, Near Marthoma Girls high school, Pulamon PO, Kottarakkara	3298191	Suresh
Kerala	Kottayam	SVM Technologies	M.P.M COMPLEX, Near Popular Maruti Show Room, M.C ROAD, S.H MOUNT,KOTTAYAM, KERALA- 686 006	2565303	Rajesh K S
Kerala	Kozhikode	Domain Infosystems	1st Floor, Al Fahad Complex, Saba School Cross Road, Near Corporation Stadium, Puthiyara, Kozhikkode-673004	0495-2722222, 0495-3243745	Mukundan
Kerala	KUNNAMKULAM	V STAR MOBILES	ROOM NO 4/ VIII/1039, CITY COMPLEX,OPP TEMPO PARK, TOWN HALL ROAD, KUNNAMKULLAM.	04885-320009	VIJUMON.K.V.
Kerala	Manjeri	Integrated Computer Systems	Royal Tower, TB Road, Manjeri - 676121	0483-3299686	Mr. Thomason Chacko
Kerala	Mavelikara	Ettutharayil Agencies	GROUND FLOOR, KOIPPALLIL ROYAL ARCADE, PUTHIYAKAVU, MAVELIKARA	3293340	Biji
Kerala	Palai	Cyriac Tv Plaza	Vypana Building,Petta Road, Palai.	329746	Tom Cyriac
Kerala	Palakkad	Benraws International	12/310/6, Ground Floor, Mero Complex, H.P.O.Road, Palakkad - 678 001.	0491-3052002	Mathews
Kerala	Pallakad	ORION TECHNO SOLUTIONS	12/310/15 FIRST FLOOR, METRO COMPLEX, HEAD POST OFFICE ROAD, PALAKAD-678001	0491 - 3200255	KHAJA HUSSAIN
Kerala	Pathanamthitta	Melamparambil Agencies	10/264, Main Road, Town,Pathanamthita	2223132	M.V. Francis Oommen
Kerala	THALASSERY	SAHAR COMMUNICATION	44-1929, MACKSON MONOR, OPP. PARIS RESIDENCY, LOGANS ROAD, THALASSERY	0490 - 3208585	AJAI
Kerala	Thiruvalla	Sangeetha Electronics	524/17, Central Tower, Cross Junction, Thiruvalla	3203000	Ranjeev Kumar
Kerala	Thiruvananthapuram	Appolo Systems	Thelungu Chetty Complex, Shop No 23-24, Kalpalayam JN Karamana, Thiruvananthapuram 695 002.	2340523	Santosh
Kerala	Thiruvananthapuram	Smart Mobile	TC 2/3554(5), First Floor, Opp. Petrol Pump, Kesavadasapuram, Trivandrum-695004	3200105	Krishnakumar P B
Kerala	Thodupuzha	National Electronics	Shop No 5, Aswathy Shopping Complex, Temple Junction, Thodupuzha	220320	Aneesh M A
Kerala	Thriprayar	Nice Mobiles	382J, 1st Floor, Century Plaza, N.H.17, Near Bus Stand, Thriprayar-680567	0487 - 3240400	T.P. Sebastian
Kerala	Tirur	Telit Telecom Shop	GROUND FLOOR, AL AMAL COMPLEX, PAN BAZAR, TIRUR	0494 - 3295623	Vasan.K.Nair

Person
-
DEEP
IRAM
h/Prem
DEEP
Lawrence
S
in
K.K.V.
nason
iac
USSAIN
icis
i
Kumar
umar P B
A A
stian
Vair

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Kerala	TRICHUR	CELL TECH	SHOP NUMBER 5B,TC23/326, N.P. TOWER, GURUVAYOOR ROAD, WEST FORT, Thrissur	0487-2387386	SANTOM KALLOOR
Kerala	Vaikom	VAIKUNDAM ELECTRONICS	II/ 214C , Mannamkeriel Complex, Bus stand Road, Valiyakavala, Vaikom	326616	Sreekumar.G
Madhya Pradesh	Balaghat	Shri Computers	Keshar Plaza Complex, Hanuman Chowk, Balaghat	9300632132	Mr. Deepak Bajaj
Madhya Pradesh	Betul	Shivam Electronics	Jiaprakash Chowk,Kothi Bazar, Auto Stand, Betul - 460001	9329099071	Mr.Vikram Motwani
Madhya Pradesh	Bhopal	Akansa Enterprises	25-26 , CENTRAL MARKET, ROSHANPURA SQUARE, BHOPAL MP	7553201626	Mr. Dinesh Asija
Madhya Pradesh	Bhopal	Neha Sales Corporation	F-104, Anmol Tower, E-5/14, Commercial Zone, Arera Colony, Bhopal-462016	7553015088	Mr.Ashok Hirwani
Madhya Pradesh	Bhopal	MUSIC MAHAL BHOPAL	SHOPNO.1 NEW MARKET NEAR HANUMAN MANDIR, BHOPAL	0755-5220725/ 2579178	Mr.SHINU
Madhya Pradesh	Bhopal	GSM SOLUTION-BHO	M-2 CHETAK COMPLEX, ZONE -2 M.P NAGAR, Bhopal	07373-316816	Mr.NEERAJ
Madhya Pradesh	Biaora	MOBILECARE-BIAORA	KR Complex Rajkand Road, Biaora. M.P.	07373-316816	Mr.Atul Sharma
Madhya Pradesh	Chindwara	Buntly Photoelectronics	Shop No.33, Jiji Bai Complex, Parasia Road, Chindwara	07162-230358	Mr.Ritesh Shukla
Madhya Pradesh	Dewas	New Taj Electronics	New Taj Electronics, 4, New Market, Moti Bunglow Main Road, Dewas	07272-220005, 406006	Mr.Shabbir Shaikh
Madhya Pradesh	Guna	Mobile Junction	Jai Stambh Chauraha,Nr.Central Bank, Guna-473001	07542-329277	Mr.Deepak Arya
Madhya Pradesh	Gwalior	Galav Computers	Ground floor ,Ganpati Plaza , City Centre , Gwalior	0751-4013311	Mr.Pradeep Dixit
Madhya Pradesh	Gwalior	VERSHA SALES & SERVICE-ASP	GROUND FLOOR SARAFa BAZAR LASHKAR,GWALIOR	0751-4060444	Mr.AJIT KUMAR
Madhya Pradesh	Indore	Apurva Electronics	UG 11 , B M Tower , Sapna Sangeeta Road , Opp. Lotus, Indore	7313207283	Mr.Nitin Kulkarni
Madhya Pradesh	Indore	Ayushi Electronics	UG-10,Ratnamani Complex, 7/1,New Palasia, Indore-452001	0731 - 3251284	Mr.Santosh Dwivedi
Madhya Pradesh	Indore	PIONEER MARKETING	224, Prem Trade Center, Maharani Road, Indore.	0731-4006503	Mr.Ritesh
Madhya Pradesh	Indore	IT CUSTOMER CARE-IND	LG-13, TRADE CENTRE,18,SOUTH TUKOGANJ, INDORE	0731-4207487	Mr. Sanjay Dhankar
Madhya Pradesh	Itarsi	S.S. Telecommunications	Vijayshree Complex 5, Line Sarafa Bazar, Itarsi - 461111	9300272505,	Mr.Akilesh Saxsena
Madhya Pradesh	Jabalpur	Sri Sai Communication	C/O MUSKAN CARD GALLERY, 766, SHAHID SMARK MARG, NEAR RANITAL SQUARE, JABALPUR-482001	0761-4046831	Mr.MOHIT SAREEN
Madhya Pradesh	Jabalpur	I T SOLUTION	GROUND FLOOR,ASTHA APPARTMENTS.WRIGHT TOWN, Jabalpur	0761 - 4014064/ 4064370	Mr.SANJEEV CHOUBEY
Madhya Pradesh	Katni	Excellent Infosys	20/306, Gurunanak Ward, Katni	07622 406047	Mr.Prafful Agrawal
Madhya Pradesh	Khandwa	NAMAN REFRIGERATION-KHANDWA	TAPAL CHALL,KHANDWA	0733-2230089	MR.YASHWANT MALI
Madhya Pradesh	Mandsaur	Sky Link Mobile Services	Payas Ice Cream Parlour, 16, Opium Godown Road, Nai Abadi, Mandsaur 458001 (M.P.)	07422-243978	Mr.Gaurav B. Mittal
Madhya Pradesh	MORENA	MOBILE PLAZA	M S ROAD , JIWAJI GUNJ , OPP BANK OF INDIA, MORENA	07532 400886	Mr.T C SHIVHARE

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Madhya Pradesh	Neemuch	Shree Balaji Mobiles	Jain Bhavan Road, Near Ganganagar Off., NEEMUCH (M.P.)	07423-320033	Mr.Savesh Goyal
Madhya Pradesh	Ratlam	Kirti Telecom	124 Station road Opp.Raj Tower, Ratlam - 457001	239346	Mr.Kirti Jain
Madhya Pradesh	Sagar	Neeta Computers	Jama Complex, Teen Batti, Sagar - 470002.	07582-329951	Mr.Ramesh Gupta
Madhya Pradesh	Satna	Maa Shaarda Communication	Gali No1, C/o Shri Gopal Sharan Singh, Pushp Raj Colony, Satna	7672320797	Mr.Prashant Singh
Madhya Pradesh	SATNA	AKASHWANI AGENCIES-SATNA	OPP.CMA SCHOOL,SHOP NO.2,ANNAM CHHAYA, REWA ROAD, Satna	07672-416455	Mr.Ajay Sukhramani
Madhya Pradesh	Shivpuri	Ocean Computer Corporation	1st Floor, Vishnu Mandir Market, Near Paniipat Handloom, Shivpuri	07492-225505	Mr.Sameer Saxena
Madhya Pradesh	Ujjain	Galaxy Computers & Communication	43/2, Varruchi Marg,Opp Madhav Nagar Police Staion, Freeganj, Ujjain	0734-2515995, 2530777	Mr.Anurag Chhajhlani
Maharashtra	AHMEDNAGAR	T V SPOT	B-3, ADARSH SAMRUDHI, NR. CHOUPATI KARANJA 414001	0241-2326267	MR ANIL APTE
Maharashtra	Akola	Supra Computers	Ushakiran Complex, Shastri Nagar, Opp. Hotel Surya, Akola.	9326866469	Mr.Prashant
Maharashtra	Amravati	Scorpio Services	Shop No. 84, Ground Floor, Gulshan Towers, Nr. Panchasheel Cinema, Amrawati, Pin-444601	0721-2567302	Mr. Pramod
Maharashtra	Aurangabad	Unique Telematics	Shop no.108/B, Behind Sajawat Handloom, Tapdiya Super Market, Nirala Bazar, Aurangabad-431001	0240-2356447	Mr.Mazhar Ahmed Shaikh
Maharashtra	Aurangabad	Electronics World	Sahyadri Building,opp. To Shivaji School,Khokadpura, Aurangabad-431001.	0240-3296998	Mr. Rauf
Maharashtra	Beed	Shree Enterprises	Behind Raj Hotel, A H Wadia Yachnalay Road, Beed-431122.	02442 231831, 02442-228855	Mr. Rahul Joshi/ Mr. Rajiv Joshi
Maharashtra	BHIWANDI	VARAD ELECTRONICS	SHOP NO2, PRABHU CHAYA BLDG, PRABHU ALI, NEAR OLD GOVT. HOSPITAL, MANDAI, BHIWANDI, DIST THANE	02522- 222653	Mr. Hitendra Zope
Maharashtra	Chalisgaon	Mobile Point	Shop-22, Momaya Complex, Near Bus Stand, Chalisgaon	02554-309996	Mohd. Israfil Ansari
Maharashtra	Chandrapur	Crystal Services	Behind Hotel Simran, Jatpura Gate Chandrapur	9370273776	Mr. Mahmood
Maharashtra	Chandrapur	Shiv Communications	Ramnagar, Near Durga Mata Mandir, Sindhi Colony, Chandrapur	329546	Mr.Maresh
Maharashtra	Chinchwad (Pimpri)	Ritz Communication	Shop No 10,"A" wing,Jai Ganesh Vision,Next to Hotel Neelkanth,Near Fam Multiplex,Akurdi, Pune-411033	020-27485613, 020 32661900, 09371029777	Ms Nikita
Maharashtra	Dhule	Pearl Communications	Below Reliance WebWorld Express, CKB Arcade, Nr Deopur Bus Stand, Dhule.	02562-324666	Mrs. Sonu Atul Bang
Maharashtra	Gondia	M/s V2 Care	Opp. Cofee house, Railtoli, Gondia 441614	329322	Mr. Krishna Sargam
Maharashtra	Hatkangale (Ichalkaranji)	Sai Vision Services	11/236 MOHAN ARCADE SHOP NO B14, STATION ROAD, TAL- HATKANGALE, CITY-ICHALKARANJI-416115	0230-2439989	Sameer Bhonsale
Maharashtra	Islampur	Solar Shoppy	opp Sai Motor Driving School, Nr Stand Road, Islampur, Distt Sangli, ISLAMPUR-415409	9326777603	Mr. D.H.Patil
Maharashtra	Jalgaon	Global Enterprises	E-81, 1st floor, Golani Market, Jalgaon -425001	0257-2236899	Mr. Pramod
Maharashtra	KALYAN	SKY LARK ASSOCIATES	Shop:1, 'A' Wing, Suresh Tower Co-op. Hsg. Soc, Opp. Municipal Vegetable Market, Santoshi Mata Road, Kalyan (W)	0251-3209899	MR. NASEER

Person	State	City	ASC Name	ASC Address	Phone No.	Contact Person
Sh Goyal	Maharashtra	Kohlapur	SMS Services	S5, Diwan Tower, Opp. Nutan Marathi School, Near Mirajkar Tikky, Kolhapur, Pin -41 6005.	0231-2541120, 9326226120	Prakash Patil
ain	Maharashtra	Kolhapur	KOMAL ELECTRONICS	517/10 "SAWALI" SHIVAJI PARK,NEAR VIKRAM HIGHSCHOOL,SHIVAJI PARK KOLHAPUR-41 6001	0231-2521424, 09823317055	MR. VASANT P. BODAKE
sh Gupta	Maharashtra	Kopergaon	Om Sai Mobile	Opp. ST Bus Stand, Dahamgaon Road, Kopergaon, Dist Ahmednagar.	02423-226463	Mr. Mahendra Devkar
nt Singh	Maharashtra	Latur	HINDUSTAN MOBILES SERVICES	Shop No.47/59,Site 110, Gandhi Market, Nr Bhalchandra Blood Bank, Main Road, Latur-41 3512	02382-641111, 982345500	Mr. Sandeep Parande
ani	Maharashtra	Malegaon	Cell Care	Shop No.14, Beside Sana Travels, Bunkar Bazar, Qidwai Road, Malegaon - 423203.	937020819	Mr Ansari Mohd Israfil
er	Maharashtra	Mumbai	Absolute Networks	A007, Vishal Shopping Centre, Next to Vishal Hall, Near Station, M.V.Road, Andheri (E), Mumbai - 400 069	022 32544800	Mr. Arun
g ni	Maharashtra	Mumbai	Creative Solutions	SHOP NO 6 AMBIKA COOPERATIVE HOUSING SOCIETY, JAWAHAR NAGAR ROAD NO 2 NEAR RAILWAY CROSSING,GOREGAON WEST, MUMBAI 400062	022-28769003	Mr. Anand
APTE	Maharashtra	Mumbai	CYBER-GYAN CONVERGENCE & SERVICES (INDIA) PVT. LTD.	43/44, Gold Filled Plaza, Sion Bandra Link Road, Sion, Mumbai-400017	022-24075939	Mr. Jatin Parekh
ant	Maharashtra	Mumbai	G.P.ELECTRONIC	A/27, Gr. floor, Sagar Tech Plaza, Andheri-Kurla Road, Saki-Naka, Andheri (E), Mumbai 400072	2232633960	Mr. MAYUR
yd	Maharashtra	Mumbai	Grace Tele Services	Shop no 3, C/1, Manik Nagar Soc, Punjabi lane, Borivali (W), Mumbai 400092	022-32455033	Mr. Daniel
ar	Maharashtra	Mumbai	Komplex Telecom Corporation	Shop no.A/19, Nootan Nagar Premises Co. Op. Hsg. Society, Near Bandra Rly. Strn., Towards Bandra Talav, Turner Road, Bandra (West) Mumbai	022 64147153	Mr. Haque
haikh	Maharashtra	Mumbai	LG Service Centre	Shop No.1,2,3 Ground Floor, Rajakamal Bldg,Opp.Ram Mandir, Subhash Road, Vile Parle(E) Mumbai 400 057	022-26134917	MR. RAKESH / OMKAR
il Joshi/ Joshi	Maharashtra	Mumbai	PARAS TELECOM	2nd floor, Rear Side Capital Cinema Building, Wauddy Road, Opp. Mumbai CST Railway Station, Mumbai	022 32022228	Mr. Ganesh
ndra	Maharashtra	Mumbai	Sai Tele Services	A-110, Satyam Commercial Complex, M.G.Road, Chhatkoper (E), Mumbai - 400 077.	022-40111264	Ms. ISHA
afil Ansari	Maharashtra	Mumbai	Yash Telecom	Dadarkar Tower, Shop no.1, Opp.Film Centre, Near Crossroads, Tardeo, Mumbai - 400 034	9324049698	Mr.Girish
mood	Maharashtra	Mumbai	TERABYTE	Shop 27, Vikas Paradise, Bhakti Marg. Off L.B.S. Road, Near R Mall, Mulund (W), Mumbai 400080	022-32640045	Mr. Chirag
sh	Maharashtra	Mumbai	Trident Communications	8-A,Vasant Smruti, Dadasaheb Phalke Road, Beside "BharatKhsetra Building", Near Dadar station(E), Dadar -East, Mumbai - 400 014.	9323960027	Mr. Kalpesh
a	Maharashtra	Mumbai	Sierra Mobiles	Opp Prabhu Darshan, L.J.Road, Shivaji Park, Near Shiv Sena Bhavan, Mumbai 400016	022 24382200	Mr. Anurag
u Atul	Maharashtra	Nagpur	Epoch Services	"Shope No. UG-9, Bhakati Vihar Complex, Chapru Nagar Square, Lakadganj, Nagpur -440008"	0712 3246777	Mr. Girish
na						
honsale						
Patil						
od						
EER						

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Maharashtra	Nagpur	Spectrum Marketing	Shop No.2, Dharampeth Towers, West High Court (WHC) Road, Dharampeth , Nagpur - 440010	712-22527823	Ms. Sonali
Maharashtra	Nagpur	Shivatronics	B-31 Sai Regency Complex Ravi Nagar Square Nagpur Maharashtra 440044	9300892579	Mr. Ravi Gupta
Maharashtra	NANDED	DEVANSH MICROTRONICS	,opp forest office, nr Ranbhikar's residence -Nanded-431602	02462-249789	Mr. Prashant Palnate
Maharashtra	Nanded	ROYAL UNIQUE SERVICES-NANDED	Plot No-48,Krishna Kamal , Opp. Sunil Furniture, Bhagya Nagar road, Ashok Nagar Nanded-431605	2,462,262,419	Mrs. Sunita Ashish Naik
Maharashtra	Nasik	Mobs Associates	Shop No. 8a, First Floor,'Kapote-Meher' Market, Renuka Nagar, Wadala Naka, Dawrka, Nasik - 422 001.	0253-6523613	Mr. Mahesh
Maharashtra	PANVEL	Oceanic Tele System	Shop No. 3, Sai Arcade, Sector 15, New Panvel (E),Dist. Raigad.	9322217221	Ms. Swapnaja
Maharashtra	PEN	SKYPHONE ENTERPRISES	SHOP NO 3, SHREE COMPLEX, OPP UNIQUE BAZAR, PEN KHOPOLI ROAD, PEN, DIST RAIGAD-402107	9373435000	MR KULDEEP
Maharashtra	Pune	MICROCHIP SOLUTIONS	Akshay Chambers 216 Naryan Peth,Near Bhide Bridge, N C Kelkar Rd, Pune-411030	020-24471155, 9823905949	Mr Mahyesh Bhosale
Maharashtra	Pune	Horizon	32A, Lotus Court, Near Hotel Panchami, Pune Satara Road, Pune.	02032501222, 9325002399	Mr. Nilesh Pundye
Maharashtra	Pune	Mobile World	G-25, AKSHAY COMPLEX, DHOLE PATIL ROAD, PUNE-411 001	30942268, 9325088055	Pawan Mantri
Maharashtra	Pune	Viki Info Technologies	Shop No4, Amit Complex,474, Sadashiv Peth,Opp New English School, Tilak Road Pune Maharashtra	020 24434134, 9322206664,09371829891	MR.VIVEK SURVE
Maharashtra	Ratnagiri	S P ELECTRONICS-PUNE	shop no-19, Parasmani Complex, K C Jain Nagar, Nr Maruthi Mandir, Ratnagiri-415612	02352-329556, 221982, 9823317158	MR. SANTOSH PRABHU
Maharashtra	Sangamneer	Rajpal Telecom	Yashodhan complex,New Nagar Rd, Near hotel Chaitali, Sangamner	02425320888	Mr Harish Rajpal
Maharashtra	Sangli	Ramesh Electronics	Opp. Kanya Purohit prashala, Rajwada, Sangli-416416	0233-2327601, 9823085176, 09372107601	Suresh Shegane
Maharashtra	Satara	Shivkal Mobilink	173/6/7 Raviwarpath shop no-11, Vithal Lila Complex, Powai Naka, opp Janta Bank, Satara-415002	02162-325212	Mr. Mahesh Shinde
Maharashtra	Shirampur	Siddharth Infocom	Shop No 1 , Hotel Sidhartha Building, Sidhartha Stop, Sagamaner Road, Shirampur-413709	02422-222117, 02422-329530	Mr. Kedar Fargade
Maharashtra	Solapur	ATHARVA ELECTRONICS PUN	940/2 NORTH SADAR BAZAR, GARUD BUNGLOW, SOLAPUR-413003	0217-2317595, 9823317081	MR. UMESH KAMALAPURKAR
Maharashtra	Solapur	Jawaharlal Radio Service	184, Gold Finch Peth, nr Hotel Ritesh, Solapur - 413007.	0217-2725030	Prasanna J Chavan
Maharashtra	Thane	Urmi Enterprises	G. F. Abhiman II , Opp. Forest Office, Teen Hath Naka, Thane (W)	022 65928384	Mr. Rinkesh Panchal
Maharashtra	VASAI	E-Link Solutions	Shop No.5, Type C, Bldg no.5/6, Shanti Vihar, Mira Road -E, Pin Code : 401107.	9322839386	Mr. OMKAR

Person
li
Gupta
iant
ta
aik
sh
naja
DEEP
esh
h
antri
SURVE
TOSH
1 Rajpal
negane
sh
r
SH
PURKAR
J
sh
AR

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Maharashtra	VASHI	BEEKEYEN ENTERPRISES	Block No 1, Shop No. 17, Mahaveer Milan, Sector 28, Near Blue Diamond, Hotel, Vashi, New Mumbai	022-65114304	Mr. Shailesh
Maharashtra	VASHI	LG Service Centre- DAKC	H Block, Ground Floor, Dhirubhai Ambani Knowledge City, Navi Mumbai-400709	022-30386032	Mr. Rajnish
Maharashtra	VIRAR	Siddhivinayak Tele Services	Shop no 5&6, Vishnu Prasad Complex, Opp Utkarsha School, Near S.T. Bus stand, P.P. Marg,, Virar (West) Pin 401305.	0250-3258111	Mrs. Yogita Kadam
Maharashtra	Wardha	Libra Electronics	Opposite to LIC office,Arvi Stand Main Road, Wardha : - 442001	245286	Ms. Manjusha
Maharashtra	Yavatmal	Star Electronics	Near Shyam Talkies Ram Mandir Road Yavatmal Maharashtra 445001	2324106	Mr.Snajay Chabda
Maharashtra	Yavatmal	Combine Electronics & Services	Shop No 13, 1st floor, Old Indira Gandhi Market, Azad Maidan Road, Yavatmal-445001	9822200166	Mr. Ajay Shukla
Maharashtra	Yeatmal	I T Services	Nr datey college,C/o Yahoo cyber cafe, Yawatmal 445001	9372610121	Mr. Umeh Gadwe
Orissa	Anugul	Creative Solution	Hanuman Bazar, Near gundicha mandir, Angul-759122	06764-329207	Mr Tapas Sahu
Orissa	Balasore	Raghunath IT Solutions	Azimabad, Proof Road, Balasore.-756001	06782-329267, 9337669107	Mr. Sujit Kr Sen
Orissa	Berhampur	Global Electronics	Gandhi Nagar, 1st Lane, Berhampur.	0680-2223124	Mr. D.B.Nepak
Orissa	Berhampur (Orissa)	RASHMI ELECTRONICS & COMPUTERS	Shop No.19, Sai Complex, Main Road, Gandhi Nagar, Berhampur, Orissa	0680-3290409	RASHMI RANJAN SHARMA
Orissa	BHADRAK	A B Associates	Nr.Reliance Web World Express, Bypass Road, BHADRAK-756001	9337040450	Kartik Chandra Rout
Orissa	Bhubaneswar	Miracle Services IT Extn.	Plot No. 136, Fr. Lane of Vigilance Office, Beh. Passport Office, Surya Nagar, BBSR.	0674-2390461, 2391533	Mr. Chaco/ Suprava
Orissa	Bhubneshwar	S.A.INFOSYS	291.Bomikhal, Opp.Akamra cinema hall, Bhubaneswar-751010	0674-2573114	Ashwini k sahu
Orissa	Cuttack	O.A.INFOTECH	Behind Govt Bus Stand, Badambadi, Cuttack -753012	9338912613	Arabind Rout Ray
Orissa	Jajpurroad	Smruti Infotech	Dala Chhak, Jajpur Road, Jajpur	06726-324529	Mr Sumit Ranjan Nayak
Orissa	PURI	Bajinath Infocomm	At Muncipal Mkt, Grand Road, Puri-752001	9337032005	Mr.Ajay/ Sandeep Agrawal
Orissa	Rourkela	Infosys	13,Bisra Road,subhadra complex Opp.Choudhary Petrol Pump, Rourkela	9337403999	Arun Ghosh
Orissa	Sambalpur	A.N.Communication	Inf. Of Zilla School, Pensionpara, Sambalpur-768001	9337660919	Mr. Md. Abdul Aziz
Punjab	Amritsar	Bajaj Telecommunication	87, G Floor, Nehru Complex, Lawrence Road, Amritsar-143001	9814650314	Suman Bajaj
Punjab	Barnala	Unique Infotech	Mittal Street, Near M C Office, Barnala-148101	01679- 238007	Pankaj Goyal
Punjab	Batala	New Krishna Entrepriese	Circular Road, Near Shekhari di Kothi, Batala	1871-396612	Navin Handa
Punjab	Bathinda	Lalli's Electronic Gallery	1139-A, First Floor, Amrik Singh Road, Nr Gole Digg, Bhatinda	0164-2239500, 2236337	Ashok Kakria
Punjab	Chandigarh	Vignesh Services	S.C.O- 189-90, Sec- 34, Chandigarh	0172-3018028	Mukesh Arya

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Punjab	Chandigarh	New Tech	SCO 495/496 SEC 35C First floor	9814244862	Mr Pawan
Punjab	Gurdaspur	S K Electronics	Ajit Singh Market, Batala Road, Nr. Petrol Pump, Gurdaspur	01874-329906	Mr. S.Sukhvinder
Punjab	Hoshiarpur	Kuldip's Mobile Care	Dhobian Wali Gali,Phagwara Road, Hoshiarpur-	01882-226906	Kuldip
Punjab	Jalandhar	Mobile Center	233/1, Saheed Udham Singh Nagar,Backside Hotel Preet, Nakodar Road, Jalandhar-144001.	0181-3292666	Vikas Sangar
Punjab	Kapurthala	Arun Electronics	217,C Block,Jama Masjid, Shoping Complex-144601	01822 329254	Arun Khosla
Punjab	Kotkapura	OM MOBILE SERVICE CENTRE	1ST FLOOR DHANU RAM PANSARI , Railway Road-151204	1635-223069, 9815759239	ROHIT MITTAL
Punjab	Ludhiana	Shahi Communication	Shop No.5, 4X International, 583 L, Model Town, Ludhiana	0161-3244190	Amit Shahi
Punjab	Ludhiana	Anant Shree Comp	19K Opp PAU Gate no 1 Ferozpur Road	0161- 3245386	Ms Monia
Punjab	Malaut	KHURANA MOBILE SOLUTION	SHOP NO 7 OPP, NEW TELEPHONE EXCHANGE G T ROAD MALUAT PIN NO = 152107	9316940003	RAMESH KHURANA
Punjab	Malerkotla	Prime Infocomm	Opp. Main gate,Govt College, MalerKotla-148023	9317731979	Rohit Bansal/Raj Verma
Punjab	Mandi Gobindgarh	Aditya Infocom	Main Iron Market, Mandi Gobindgarh	9316320490	Naresh Aggarwal
Punjab	Mansa	Sharma Telecom	OPP.PARKASH BOOK DEPOT,NAGINA MARKET, MANSA	9316173009	Udesh Kumar Sharma
Punjab	Moga	Rashpal Telecom	6, Red Cross Road, Court Road, Near Old Court, Moga-142001	01636-222468	Mr. Rashpal Singh
Punjab	Nabha	Echo Telecom	Opp. Milan Palace Circualr Road. NABHA 147201	01765-329244	Girish Garg
Punjab	Nawasher	Kapoor Electronics	Kothi Road, Opp Kumar Hotel, Nawashahr-144514	01823-509739	Narender Pal
Punjab	Pathankot	Touch InfoSys	189 Opp. Guru Nanak Park, Model Town, Pathankot.	0186-3290300	Mr.Navdeep Singh Bedi
Punjab	Pathankot	Leo Comp	Near Tourist hotel, military ground, Pathankot	9814586406	Mr Kamal
Punjab	Patiala	Image Services	84, First Floor, Leela Bhawan, Patiala-147001	0175-2222796, 9872281524	Rohit Bansal
Punjab	Phagwara	Bansal telecom	G T Road,Railway Road Chowk, Phagwara-144401	01824-461321, 9888005339	Mangalesh
Punjab	Rajpura	M K Enterprises	Shop no.6,Gurudwara Singh Sabha Market, Rajpura Town-140401	9316432866	Johny
Punjab	Ropar	Arora Communication	Shop No.1,Lehari Shah Mandir Road,Ropar	9872363032	Amit Arora
Punjab	Samana	Sangam Mobile care	Tehsile Road,Near Garg Laboutry	9316868292	Vaneet Kumar
Punjab	Sangrur	NATIONAL COMPUTERS	SUNAMI GATE, SANGRUR PIN NO = 148001	1672233335, 9814586196	SARABJIT SINGH
Punjab	Sarhind	A.S. Infocom	Grain Market,Cinema Road Sirhind City-140406	01763-324777	Jaspreet Singh
Rajasthan	Ajmer	Nehal Infotech	S1, 2nd Floor, Inderlok Complex, Near Agra gate, Ajmer	3291404	Suresh sharma/ Shatrugan
Rajasthan	Ajmer	Prangan	112/10,Civil lines,Ajmer		Pareek

Person
n
khvinder
ngar
psla
MITTAL
hi
a
JA
nsal/Raj
vggarwal
nar
pal
arg
r Pal
eep
di
il
nsal
sh
ra
kumar
T SINGH
Singh
harma/
in

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Rajasthan	Alwar	R.K.Telecom	SHOP NO.112, FIRST FLOOR, GANPATI TOWER NEAR NANGLI CIRCLE , Alwar		Umesh sharma
Rajasthan	alwar	Pareek electronics	Opp. To Tehsil,Alwar		Pareek
Rajasthan	Beawar	Srikrishna Infocom	Chaoni Road, Bhagat Chauraha, Near Roadways Bus Terminus,Beawar	329675	Shravan
Rajasthan	Bhilwara	Ajanta Communications	No3,Bapna Complex,Pur Road,Bhilwara	9351610212	Shravan
Rajasthan	Bikaner	Tech Solutions	1st floor,222&223, Ganpati plaza, KEM Road, Bikaner	3292423	Aziz/Vika
Rajasthan	chittorgarh	Arihant Infotech	A46,Meera Market, Near Rajasthan Patrika Office, Chittorgarg	325933	Abhishek
Rajasthan	chomu	Tambi Telelink	Kotwali chabutra, dhan ji ki gali, Sadar Bazar Chomu	9314090400	Anup tambi/DP Saini
Rajasthan	Dholpur	Tirupati Telecom	14,Bhagwati Market, Near Jagan Cinema hall, Jagan Tiraha,Dhoulpur		Moshin/ Devender
Rajasthan	Jaipur	Alpha Infotech Systems	F-1, First Floor, Krishna Mall, Lakshmi Mandir Crossing, Tonk Road, Jaipur-302015	3299724	Shatrugan mangal
Rajasthan	Jaipur	Vishwas Infotek	13-14,Indira Switch, Opp Chambal Power House, Hawa Sarak,Civil Lines, Jaipur-302016	3242050	Madan
Rajasthan	Jaipur	Alliance Communication	G6,City plaza,Space Cinema Hall, Jhotwara Road, Jaipur-16		Amit/Bhushan
Rajasthan	Jaipur	Solution Computers	Plot no4,Krishna nagar II, Janpath, Lalkothi, Near Hotel Paradise, Jaipur.		Dhreej mathur
Rajasthan	Jhunjunu	M S Mobile Point	Shop num.5,Kaswan Complex,Opp Roadways Bus Stand,Jhunjunu		Abhshek/Sunil
Rajasthan	Jodhpur	Omega Electronics	UG/4, Adeshwar Tower, Main Chopasani Road, Opp.Gehlot Watch Co, Jodhpur-342003	3291214	Pratap singh
Rajasthan	Jodhpur	Space Electronics	Shop no4, Manidhari Hospital, Residency road, Jodhpur	3291214	Hemanbt
Rajasthan	Jodhpur	Digital electrocare	3/4B, 1st Polo Pawta,Jodhpur		Johender
Rajasthan	Kishangarh	Capital Enterprises	5,Radha Krishna market, Opp. Sardul school, Kishangarg	326550	Sharrugan
Rajasthan	Kota	Cyber Infosystems	26, Ground floor, Kalawati Paliwal market, Gumanpura, Kota-324007	232153	Rais khan
Rajasthan	kota	Rajesh electronics	355,Shopping centre,Near Jain Mandir,Kota		Rajesh
Rajasthan	Kota	Saya electronics	1-TA-16,Vigyan Nagar,Kota		Lalit
Rajasthan	Kotputli	Isha Communications	11, ground floor, Govardhan plaza, Nehru Bazar, Kotputli		Vijender
Rajasthan	Nagaur	Jam Appex	Shop num.7, Opp. Old power house, Station road, Nagaur	329595	Amit
Rajasthan	Nathdwara	Geniune Infotech	Shop num.10,Suriya apartments, Opp.Vandana talkies, Bus stand, Nathdwara.	329208	Gajender
Rajasthan	Pali	Mansi Mobile	9,Vasant Vihar,Opp. Bangur college,Pali		Abhishek
Rajasthan	ShrigangaNagar	Telecare Servecies	33J Block, Near Birbal Circle, SriGanga nagar	3207687	Abhishek
Rajasthan	ShrigangaNagar	Electro device care	10 H Block, Sri Ganga nagar.		Raman choudhary
Rajasthan	Sikar	Rita Computers	ShopNo4, Kabra Market, Shramdan Marg, Sikar		Saurav chakravarthy

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Rajasthan	Udaipur	Ficusa Enterprises	13,Darshanpura,Opp.M.B.Commerce College Gate, Nr Computer Zone,Udaipur-313002	2410002	Mahak/Virendra
Tamilnadu	Ambasamudram	THE MOST TECH	63D , k.n.v.complex, Opp to Marichamman Temple , Ambasamudram	04634-251143	mr.stany
Tamilnadu	Arkonam	G.M. MARKETING	NO.3/4, SUBURAYAN STREET, ARAKKONAM-631001	04177-231395	Mr. p.gajapathi
Tamilnadu	Arni	Digitech Computers	Shop No. 201/82- B1, SM Road, Arani - 623101	04173-223929	d.mohan ram
Tamilnadu	Aruppukottai	THE MERCURY COMPUTERS	607, MADURAI ROAD, NEAR NEW BUS STAND, ARUPPUKOTTAI-626101	04566-222552	Mr. R.BOOMINATHAN
Tamilnadu	Attur	VRNET	V.R.Net,Dr.Arumugam complex,salem main road ,ATTUR	04282-243585	Mr.Senthil kumar
Tamilnadu	Batlagundu	Karthik Communications	No 221 , Main Road , Batlagundu- 624202	9360019090	Mr Lakshmanan
Tamilnadu	Bhavani	Sri Abirami Electronics	2E , Pavadi Street, Anthiyur Corner, Bhavani-638301	04256-230919	Mr Balamurugan
Tamilnadu	Chegalapatu	SKB Electronics	No-42 Devarajanar pillai Street, Vedachalam Nagar, Chengalpet	044-37406080	Mr.Balaji
Tamilnadu	Chennai	Genesis Communication	63/3, First main road, Gandhi Nagar, Adyar, Chennai-600020	044-24401188	Mr Suresh
Tamilnadu	Chennai	GS Systems	547/352, F M Towers, Mount Road, Nandanam, Chennai-600035	044-24330889	Mr.Nicholus
Tamilnadu	Chennai	Sabisu	B2, Golden Enclave, New 275, Old 184, Poonamallee High Road, Kilpauk, CHENNAI 600 010.	044-26612347	Mr.palani
Tamilnadu	Chennai	Unicare Infocomm Services	No.293, Arcot Road, Next to Indian Overseas Bank, Kodambakkam Chennai - 24	044 24724666, 044 52047059, 09382306857	Kartik
Tamilnadu	Chennai	GARAGE DE TELECOM	OLD No:30: NEW No: 10, KMBF BUILDING,1ST FLOOR, DURAISAMY ROAD, NEAR POTHYS,T.NAGAR, CHENNAI 600017	044-28143454	
Tamilnadu	Chidambaram	Future Tech	Hasan Towers, 1st Floor, No. 14, V.G.P.Street, Near Hotel Ritz, Chidambaram	04144-222150	Mr.Shaker
Tamilnadu	Coimbatore	Fast track	138-C, TV Swamy Road (West) , RS Puram , Coimbatore - 641002	2551155 ,	Mr Anand
Tamilnadu	Coimbatore	Nucom Services	3/61, Master Building, Kattoor Road, Pappa Naicken, Palayam, Coimbatore - 641037.	4351569	Mr.Uthaman
Tamilnadu	Coimbatore	Classic Electronics - Coi,	No 1/1 , Alagappa Road , 6th St, Tatabad, Coimbatore - 640012	4374875	Mr Arivazhagan
Tamilnadu	Cuddlore	Kasturi Cellular Service	NO: 37 (2C) BHARATHI ROAD, CUDDALORE. 607 001, CUDDALORE DISTRICT,TAMIL NADU.	04142 - 220183	Mr Raghupati
Tamilnadu	Cumbum	LG MOBILE SERVICE GALLERY	No 52, Gandhiji Street, CUMBUM-625516	9360211100	Mr.Senthil kumar
Tamilnadu	Dharapuram	IT Zone	40-A-1, Bye Pass Corner, Dharapuram-624202	9360360779, 04258-329293	Mr Ramakrishnan
Tamilnadu	Dharmapuri	CALRITY DIGITAL PHOTO&AUDIO	98/29C KANDASAMY VADIYAR STREET, DHARMAPURI, 636701	04342-265835	MR. RAJ MURUGHESAN
Tamilnadu	Dindigul	padma electronics	15,Dudley high School, Dindigul	0451-2427080	murali chandra
Tamilnadu	Erode	Jans Electronics	29, Sathy Road, Near Hotel Oasis, Erode - 638004	3258526	Mr Kannan
Tamilnadu	Gobichettipalayam	BEST ELECTRONICS	47a/1, kms complex kacherry medu, gobichettipalam	04285-225598	Mr. g.a.jayakumar

Person	State	City	ASC Name	ASC Address	Phone No.	Contact Person
irendra	Tamilnadu	Hosur	Suryas will of people	R S Towers, Opp Traffic Police Station, Bangalore By Pass Road, Hosur-635109	04344-246687	Shanmugam
	Tamilnadu	Kallkuruchi	NEW MAGESTIC CELL SALES&SERVICE	OPP TO TELEPHONE EXCHANGE, GANDHI ROAD KALLAKURICHI	04151-228270	MURUGESAN
apathi	Tamilnadu	Kancheepuram	Classic Mobile Care Centre	Door No.67-A, (Shop No.5), P.S.K. Street, Kancheepuram-631 501	9345636900	Mr. Damodaran
ram	Tamilnadu	Karaikal	SHREE HARINI CELLULOR SERVICE	OPP. TO NEW BUS STAND , BHARATHI MAIN ROAD,KARAIKAL- 609602	320544	K.SELVACANAPATHY
NATHAN	Tamilnadu	Karaikudi	SITIYES ELECTRONICS	10 A / 3 , Muthulakshmi Complex, Opp to Income Tax Office, Sekkalai, Karaikudi - 630002	9362611455	Mr.S.VEEERAPANDIYAN
il kumar	Tamilnadu	Karur	Aswathi Electronics	108 ,Old Bye-pass Road , Near KG Hospital , Karur	9360244555 , 9367123748	Mr Satish Kumar
imanan	Tamilnadu	Kovilpatti	ST.MARYS CELLPHONES	No.6, Rajakumari Towers, AKS Theater Road, Kovilpatti	9360533649 / 9894133839	Mr. Iyyappan
	Tamilnadu	Krishnagiri	Madura Care Centre	No 361, Crown Complex, Bangalore Main Road, Krishnagiri-635001	9364258223	Mr Suresh Kumar
h	Tamilnadu	Kumbakonam	FARGAN ELECTRONICS	NO.5 VRS COMPLEX, HAJJAR STREET, KUMBAKONAM- 612001,	0435-2401123, 3290303	SURBUDEEN
ylus	Tamilnadu	Kuzhithurai	Mobile Care	Shop no 211 , SM Arcade, Main Road, Marthandam , Kuzhithurai - 629165	270587	Mr Surendra Kumar
i	Tamilnadu	Madurai	Devaa Electronics	No.4, Thirumakulam North Street,Near Ayyappan koil, Thhallakulam, Madurai-625002	4360995	Guna
	Tamilnadu	Mayiladuthurai	NRS MOBILE CITY	NO-28 - C/14 , R.R.COMPLEX, MAILADUTHURAI	04364-223277	ABDUL RAHIM
	Tamilnadu	Nagercoil	Redeemer Electronics	Shop no 2, Pillars Gate, Balamore Road, Nagercoil-629001	04652-327788, 9443453490	Mr.Dinkar
	Tamilnadu	Namakkal	V.R CARE	77/2, Veera Vilas, Trichy Main Road, Namakkal - 637001	04286-329304	Mr. R.Vijayalakshmi
3r	Tamilnadu	Ooty	MOUNTAIN CELL COM	NO:302,Band lane, Commercial road,Near Liberty Theatre, Ooty- 643001.	0423-2443787	Mr.Sujith & Miss . Geetha
d	Tamilnadu	Palani	HI-TECH ELECTRONICS	No.76, New Dharapuram Road, Opp. ICICI Bank, Palani - 624601	04545-240244	Mr. r.ramachandran
nan	Tamilnadu	Paramathy Velur	Vishwak Mobiles	No 5, KK High School Building, 98, High school Road, Paramathy Velur - 638182	04268-224348, 9360110755	Mr Mohan
zhagan	Tamilnadu	Pattukottai	MOBILE CARE	127, BIG STREET, PATTUKOTTAI	04373-252150	MR.ARUL ALAGAN
upati	Tamilnadu	Perambalur	THE BEST	Vivkanand st., M.P. office opp., Perambalur	04328-275717	Mr.P.Kumar
il kumar						
krishnan						
HESAN						
andra						
an						
yakumar						

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Tamilnadu	Perundurai	SREE BABY ELECTRONIC	483, mainroad, perundurai	04294-221800	Mr.shiva balan
Tamilnadu	Polachi	STAR MOBILES	SHOP NO. 5 Ground Floor, Vasanth Complex, Immamkan Street, POLLACHI.	04259-222230	Mr.Senthil Kumar
Tamilnadu	Pondicherry	Digital Logistics	126/2, Perumal Koil Street (Bharathi Street Cutting), Pondicherry-605001	9843093348	G Singaravelu
Tamilnadu	Pondicherry	BALAJI ELECTRONICS (ASC)PON-CHE	No:21, 3rd CROSS STREET, Annanager, PONDICHERRY	3090414	
Tamilnadu	Ponneri	SRI BALAJI MOBILE CARE CENTER	NO, 26, THALUKKA OFFICE ROAD, PONNERI, THIRUVALLUR DIST-601204	27973381	Mr.BALAJI
Tamilnadu	Port Blair	UNIVERSAL SERVICE CARE	R.G.T. ROAD, PORT BLAIR, ANDAMAN-744101	03192-329588	Mr.Naveen
Tamilnadu	Pudukottai	YEM KAY ELECTRONICS	2, Subabharathi complex, 5378, 79, Alangudi Road, Pudukottai-622001.	9344038441	Mr.Rajesh Kannan
Tamilnadu	Rajapalayam	SRI VIGNESH MOBILES	292\1, TENKASI ROAD, OPP BOMBAY LADGE, RAJAPALAYAM-626117	04563-220398	Mr. KU.G.MUTTHIAH
Tamilnadu	Ramanathapuram	ZEENATH TELECOM	13-B/23, PAL LUCKY PLAZA, Madurai Road , RAMANATHAPURAM-623501	04567-226750	Mr.M.S.JAHIR HUSSAIN
Tamilnadu	Ranipet	Unicare Infocom Services	No.36, opp.Gangadhara Muddaliar Middle School, MBT Road, Novelpur,ranipet, Vellore Dist.	270806	Mr.Basker/ Mr.karthik
Tamilnadu	Rasipuram	SMS CARE SERVICE	No 179 / 1, Anna Salai, Ground Floor, Rasipuram-637208	9345052553	Mr Manikavasagam
Tamilnadu	Salem	Vishwesh Mobiles	Sixer Complex, 121/19A, Sarada College Road, Next to Abi Medical Centre, Salem - 636007	3290535	Vasudev Nayak
Tamilnadu	Sivakasi	TELE WORLD	78, PARSN PLAZA, Chariman Shanmuga Nadar Road , OPP.TO.WATER TANK, SIVAKASI-626123	04562-325730	B.MATHAN KUMAR
Tamilnadu	Tambaram	SARAVANAS INFOCOM SERVICES PVT LTD	New No-43 ,Old No:3A,Mudichur road,Tambaram west,chennai 600045	044-32915599	Mr.Palani/ Mr.ranjith
Tamilnadu	Tenkasi	AIRTONE	1/ 17, KMSS complex, west masi street, Tenkasi. 627811	04633-227980	Mr. M.Nagaraja sankar
Tamilnadu	Thanjavur	Z M Electronics	1006/1007, South East Rampart, Opp to Municipal Higher Sec School Tanjore - 613001	272595, 329554	Ziauddin
Tamilnadu	Tindivanam	REVA COMMUNICATIONS	Old No. 117/1, New No. 205/1, Nehru Street, Tindivanam - 604001	225250	LAKSHMI NARAYANAN
Tamilnadu	Tiruchendur	ARK MOBILE SOLUTIONS	ARK DTP centre, No. 1 a 7 North car street, Rayan Complex, Tiruchendur. 628215	04639-243339	Mr.Mahesh
Tamilnadu	Tiruchengode	BALAJI ELECTRONICS	108 s s d road,near lorry stand tiruchengode	04288-255157	Mr.sekar
Tamilnadu	Tirunevelli	Classic Electronic	39, Trivendrum Road, Opposite Kalimark, Welcome Complex, Palayamkottai, Tirunilveli-627002	2575801, 3290339	Erkins
Tamilnadu	Tirupattur	Acal Computer Systems	52/1, kkc complex, krishnagiri road, tirupattur	325385	sunder
Tamilnadu	Tirupur	Shri Vasavi Electronics	"# 155-303, Mangalam Road, Karuvam palayam, Tirupur -641604"	4244009	MR.U.B. Bala Murali

Person
balan
il Kumar
avelu
Jl
n
h
JTTHIAH
AHIR
n
r/
ik
avasagam
Nayak
AN
i/
h
agaraja
I
NAN
sh
Bala

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Tamilnadu	Tiruvapur	Softel Teleservices	No 21 , Municipal Complex , Ground Floor , Panagal Road , Tiruvapur-610001	04366- 22110, 9362721444	Mr Ravi
Tamilnadu	Tiruvellore	Yamkarna Computer	38/186 JAWAHARLAL NEHRU ROAD, OPP TO SBI MAIN BRANCH, THIRUVALLUR - 602 001	37600329	Mr. Saravana
Tamilnadu	Trichy	S K Electronics	Raj Complex, 9/A EVR Road, Puthur, Trichy- 620017	277,194	Krishnan
Tamilnadu	Tuticorin	Snows Cell Care	Kala Complex, No 20,B-1,W G C Road, Tuticorin-628002	0461-2334043	Kennedy
Tamilnadu	Udumalpet	ALLWA ELECTRONICS	5 Thuluva vellar shopping complex, V.O.C. street,UDUMALPET.642126	04252-223047	Mr. Sentamarai kannan
Tamilnadu	Vaniambadi	REVA COMMUNICATIONS	No.848/3, CL Road, Vaniambadi - 635 751	395023	LAKSHMI NARAYANAN
Tamilnadu	Vellore	Matha Communication	4, S.L.N Plaza, Opposite Odai Pilliar Koil, Gandhinagar,Vellor - 632006	0416-2240800	Gunaa Shekhar
Tamilnadu	Villupuram	BROAD BAND	no 642, nehruji road, VILLUPURAM	222936	Mr. Pragasam
Tamilnadu	Virudhunagar	RBG Electronics	76/9, Lakshmi Complex, Pullalakkottai Road, (Opposite Uzhavar sandhai), Virudhunagar-626001.	04562-420160, 9344869593	Mr Karrupuswamy
U.P. (East)	Barabanki	Yash Enterprises	Rashid Enclave, Mugal Darbar, First Floor,nagar palika rd, Barabanki	9336323714	Mr. Ajay Srivastava
U.P. (East)	FAIZABAD	Microworld Computer Hardware Lab	1st floor, Baldev Plaza, Rekhabganj, Faizabad	9335098244	Kapil/Sunil
U.P. (East)	Fatehpur	TRIMURTI TELECOM SERVICES	230, SHADIPIR CHAURAHA, NASEPEER ROAD,FATEHPUR-212601	9336223093	Sanjay Sachan
U.P. (East)	Gonda	DIGITECH SERVICES	Suraj Complex Malviya Nagar, Ground Floor,In front of Distt. Mahila Hospital, Gonda	9336695719	Atul Singh Chauhan
U.P. (East)	HARDOI	Shipra Electricals & Appliances	553 STATION ROAD, RAILWAY GANJ, HARDOI-241001	9335348407	Gaurav
U.P. (East)	JHANSI	Krishna Enterprises	372/A CIVIL LINES,GWALIAR ROAD, JHANSI-284001	9335090997	SUJEET
U.P. (East)	Kanpur	AAKARSH ELECTRONICS	63/2 C(9)BALAJI COMPLEX, THE MALL, KANPUR	9335360303	Mr.Raman
U.P. (East)	Kanpur	AR Infotech	111/402 Ashok Nagar, Kanpur Pin 208012		Amit Trivedi
U.P. (East)	Kanpur	LB Infotech	124/122A GOVIND NAGAR, KANPUR	0512-3207303	Deepak Bhatia
U.P. (East)	LAKHIMPUR	S S ELECTRONICS	GURDARSHAN BUILDING, KACHEHRI ROAD, LAKIMPUR KHERI, LAKHIMPUR -262701	9335038258	SAURABH SINHA
U.P. (East)	Lucknow	ALFA ELECTRONICS	Shop No.GF20 ABC Complex, Kanpur Road, Lucknow	0522-3948730	Harjinder Singh

State	City	ASC Name	ASC Address	Phone No.	Contact Person
U.P. (East)	Lucknow	Hitech Communication	SS 205, Road Cross Plaza, Badshah Nagar Crossing, Lucknow.	9335088061	MR.RAVI PRAKASH/ MR.RAJENDRA RAMAN
U.P. (East)	Lucknow	NET COM	3 way road, City Point, Opp Krishi Bhawan, Lucknow-226024	0522-3094222	Vinod Sharma
U.P. (East)	Lucknow	RR ENTERPRISES	Shop No.3,first floor, Deewan Chand Complex, 292/11 Chowk, Lucknow	0522-3262263	MR.YOGESH
U.P. (East)	Lucknow	MOBILE DOT COM	G2 Shri Ram Towers Ashok Marg ,Lucknow	9335819202	Mr Anand Jhouri
U.P. (East)	Raebarilly	Karuna Enterprises	Shop No.3, Bajpai Market, Beliganj, Maik Main Road, Raeberilly	9336005741	Vikas
U.P. (East)	Sitapur	Higrade Computers	7, Muncipal Market, Sitapur	05862-351808	Sanjeev Goel
U.P. (East)	SULTANPUR	S S INFOCOM	SHOP NO. 14&15 NANDINI COMPLEX NEAR SUPER MARKET SULTANPUR-228001	9335055217	SACHIN DWIVEDI
U.P. (East)	Unnao	Avijit Infocom	251 opp Collector Ganj, Unnao	0512-6820020	VISHNU PANDEY
Uttar Pradesh	Agra	NSC Computers	Shop No G-124, Block No- 29, Sanjay Place, Agra --	9319111350	Rajeev Singhal
Uttar Pradesh	Agra	Ankur Care Centre	6/1, M.G.Road, Agra.	9412254152	Ankur Goyal
Uttar Pradesh	Agra	Space Consultancy & Services	UG 1 & 2, Opp. Jaihind Hotel, Merchant Chamber, Sadar Bazar, Agra	9358504140	Kapil Sharma / Rihan Pervej
Uttar Pradesh	Aligarh	Infocare	17, Vikram Arcade, Railway Road, Aligarh -	9359588880	Kamal Jain / Prabal bansal
Uttar Pradesh	Aligarh	A.V.Computer Services	City Enclave opp.Kumar Nursing Home Ramghat Road	9412274391	Vaivhav Gupta
Uttar Pradesh	Allahabad	RADIO CENTRE	SHOP NO-3 1ST FLOOR MEENA BAZAR, Allahabad	3292488	MR. MANISH KHANNA
Uttar Pradesh	Allahabad	B.P.Electronics	28, M.G.Marg, opp Rama Jewelers Civil lines, Allahabad-211001	3290315	Mr. Umesh Aggarwal
Uttar Pradesh	Allahabad	MICRONET SOLUTION	B 38/1 ,SHOP NO. FF3 VASHITSTHA VINAYAK TOWER, TASHKAND MARG, CIVIL LINES, ALLAHABAD	9335395183	Mr. Hashmi
Uttar Pradesh	AMROHA	SHREE JEE TRADERS	KAILS ROAD NEAR MODABADI GATE, AMROHA	9319075289	SIDHARTH AGARWAL
Uttar Pradesh	AZAMGARH	RAJASTHALI	ASIF GANJ, CHOWK, AZAMGARH-276001	223644	MR.TRILOKI NATH JALAAAN
Uttar Pradesh	Badyun	Customer Care Services.	Plaza Market 1st Floor Near Ghantaghar sixroad Badyun.	9319086944	Mr. Nazim
Uttar Pradesh	BAILA	Sankatha Communications	Mall Godam Road Dr.S. N.Pandey Clinic Chowk Balia-277001. UP	9336635533	Mr. Manish
Uttar Pradesh	Bareilly	JAI INFOTECH	SA-96 DEENDAYAL PURAM BAREILLY	0581-3208484	Mr Rohit Tandon
Uttar Pradesh	Bareilly	Sapan Infotech	G - 64 A Kunwar Complex, Near Gupta Watch Co,116 Civil Lines, Bareilly	9359102467	Mr. Dharendra Negi
Uttar Pradesh	Basti	Royal Enterprises	Shop No.12 Nagar Palika Market, Company Bagh, Basti	9336784054	Sunil Kumar
Uttar Pradesh	BHADOI	Kislay Communication	VINDA MARKET NEAR TEHSIL, BHADOI-224101	9235506029	KISLAY
Uttar Pradesh	Bijnor	Konark Service Centre	Shop No.7,1st Floor, Near Ajaz Ali Hall, Nagar Palika Complex, Bijnor.	9358364067	Mr.Pratyush Gupta
Uttar Pradesh	Bulandshar	MN Telecom	Shop No-1 BHARAMAPUTRA COMPLEX,KALA AAM, BULANDSHAR	9,358,011,688	Mr Taukir Khan

Person
PRAKASH/
DRA
arma
ESH
d Jhouri
Goel
I
PANDEY
nghal
oyal
irma /
rvej
n /
ansal
Gupta
NISH
A
sh
imi
H
L
OKI
LAAN
n
sh
Tandon
endra
nar
ish Gupta
r Khan

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Uttar Pradesh	CHANDOUSI	OM TECHNOLOGIES	697, SITA ROAD,NEAR GANESH MANDIR, CHANDOUSI	9359986766	SACHIN GUPTA
Uttar Pradesh	DEORIA	ATHARAV COMMUNICATION	SHOP NO 5,SHANTI COMPLEX, HANUMAN MANDIR ROAD	9305012566	K.N.GUPTA
Uttar Pradesh	Etah	Triveni Computer Service	688/1 Vijay Nagar,Infront of Shraddha Cinema, Thandi Sadak, Etah-207001	9719398761	Vinod Kumar
Uttar Pradesh	Etawah	Frontline Computer	132, Sivil lines, Pakka Talab X-ing, Opp. HeroHonda Showroom, Etawah-206001	9219404194	Mr.Puneet Kaushik
Uttar Pradesh	FARRUKHABAD	WAVE TECHNOLOGIES	2 B /122 AVAS VIKAS, LOHIA PURAM, FARRUKHABAD-209625	9335921175	DHARAMVEER
Uttar Pradesh	Ghaziabad	Charu Enterprises	Shop No.15,Opp. Sales Tax Check Post, G.T.Road,Mohan Nagar	0120-3223417	Mr.Chander Shekher
Uttar Pradesh	Ghaziabad	Concessionair Documentation India Pvt Ltd (CDIL)	C-83, Rajnagar District Center (RDC), Ghaziabad	0120-3292011, 4102418	Anil Tiwari
Uttar Pradesh	Ghaziabad	AZURE SYSTEMS	F-28 Konark Building, RDC, Raj nagar GZB	0120-2700717	Mr. Aseem Saraswat
Uttar Pradesh	Gorakhpur	Eternal Electronics	Shop No.11, Pandey Complex, 33, Kasya Road, Opp DIG Bunglow, Gorakhpur -273001	3250395	Mr. Ajith
Uttar Pradesh	Gorakhpur	MM Communication	Udai Trade Centre, Opp Dr H.N.Singh Medical College, Basharatpur, Gorakhpur	3250395	Mr.Ashwani
Uttar Pradesh	Hapur	SMART SOLUTIONS	10, 1st Floor,City Plaza , Hapur, Ghaziabad - 388001	9319384063	Mr.Rajkumar Kanaojia
Uttar Pradesh	Hathras	Arya Electricals	Bldg No.2206,Near Mayfair Hotel, Kamla Bazar, Hatras-204101	9319338655	Mr.Suneet Arya
Uttar Pradesh	Jaunpur	Shubham Pustakalya	Mandi Naseeb Khan, Near Siya College,Jaunpur	9336510130	Sudhir/Sanjay
Uttar Pradesh	Jaunpur	SUPREME COMMUNICATION	J.P. Complex, Oland Ganj, Jaunpur	9235407278	Mr.Mahatab Raja beg
Uttar Pradesh	Kannoj	DIXIT MOBILE LAB	SHOP NO. A1 WARSI COMPLEX, LAKHAN TIRAHA, KANNOJ	9335042373	SUNIL DIXIT
Uttar Pradesh	Khatauli	Sigma Systems	A-6,Shivlok Market,Near Indra Murti, G.T.Road, Khatauli	9412582668	Mr.Alok Kumar
Uttar Pradesh	Mainpuri	Raj Communication	1002, Sadar Bazar, Near PNB , Mainpuri-205001 (U.P)	9358090251	Mr.Rishabh Khirbat
Uttar Pradesh	Mathura	R K Infocare	G-1, Atithya Palace, Sonkh Adda, Junction Road, Mathura-	9319999666	Alok Gupta
Uttar Pradesh	Meerut	Care Centre	G-19 , Vardaman Plaza, Garh Road, Meerut.	0121-3249666	Mr.Ajay Mittal
Uttar Pradesh	Meerut	Systech Computers	F-124/125 1st floor Ganga Plaza, Begum Bridge Road, Meerut.	0121-4003194	Vineet Goyal
Uttar Pradesh	Meerut	COINCAP SERVICES	Labour Compound, Above Allahabad Bank,Near Akash Ganga Jewellers, Begum Bridge, Meerut	0121-2667942	Atul Mittal
Uttar Pradesh	Meerut	Essar Services	F-122/123 1st floor Ganga Plaza, Begum Bridge Road, Meerut.	4024894	Rajiv Gupta
Uttar Pradesh	MIRZAPUR	MOBILE ZONE	RAM MARKET, PASARHATTA BAZAR, MIRZAPUR-231001.	9335785979	MR.Anup
Uttar Pradesh	Modinagar	ANANYA COMMUNICATIONS	24,K.N.MODI COMPLEX, Modinagar-201204	01232-325424	Mr.Nitin
Uttar Pradesh	Moradabad	Bhavya Technologies	A12, 1st Floor, Rampur Road, Gandhi Nagar, Moradabad	0591-3292318	Vivek Kumar Singh

State	City	ASC Name	ASC Address	Phone No.	Contact Person
Uttar Pradesh	MUGALSARAI	SKY MOBILE WORLD	SUPER MARKET,MUGALSARAI	255505	VIBHUTI JAISWAL
Uttar Pradesh	Muzaffarnagar	ADVANCE SERIES	Shop No-15 prakash chowk Muzffarnagar-251001	09412210142	Mr. Rajiv
Uttar Pradesh	Muzaffarnagar	Jai Computers	Shop No. 4, 1st Floor, Roorkee road, Near Shiv Chowk,Central Bank Mkt, Muzaffarnagar-251001	0131-3294447	Manohar Singh
Uttar Pradesh	Noida	M R Telecom	D-329, Sector 10, Noida, (Corner Building, Noida Stadium - Jhundpura Main Road)	0120-4312715	Kailash Aggarwal
Uttar Pradesh	Pilibhit	Kamal Electronics	Station Road, Pilibhit	9319911226	Mr. M A Jillani
Uttar Pradesh	PRATAPGARH	CHANDRA PRATAP VEER & CO	KATCHERY ROAD, CHOWK BAZAR, PRATAPGARH -230001	9335048271	RAJESH AGARWAL
Uttar Pradesh	RAMPUR	MAMTA TECHNOLOGIES	OPP,JILA PANCHAYAT OFFICE, RAHE RAZA, RAMPUR	9319347583	RAJEEV YADAV
Uttar Pradesh	Saharanpur	Maharaj Communications	Near Maharaja Palace,Delhi Road, Saharanpur	0132-2720881	Pankaj Malhotra
Uttar Pradesh	Shahjahanpur	Sunny Mobile Point	258 B TARIN BAHADURGANJ, SHAHJANPUR	9335019616	Rajaram Maurya
Uttar Pradesh	Varanasi	Jaiswal Electronics	S6/107 KACHAHRI CROSSING,NEAR COURT, VARANSI	3200375	Mr.Sujeet
Uttar Pradesh	Varanasi	Shivam Mobile Distributers	Shop No.5,B37/115-B-1 Baradari Complex, Rathyatra Crossing, Varansi Pin 221010	933540000	Rishi Mohan
Uttaranchal	Almora	Kumar Telecommunications	Paltan Bazaar, Almora	9411525789	Mr. S Kumar
Uttaranchal	Dehradun	Krishna Communication	Shop No 15A, Meedo Plaza, Rajpur Road, Dehradun,Uttaranchal.	0135 3290895	Vinod
Uttaranchal	Dehradun	PROMPT SERVICES-DEH	133, Old Connaught Place, Dehradun	9359903573	Mr. Bipin
Uttaranchal	Haldwani	Fairdeal Agencies	1st Floor,Nainital Road,Uttaranchal Trade Centre,Tikonía Chouraha, Tikonía, Haldwani	09359136000	Mr.Ajay Gupta
Uttaranchal	Haridwar	Maharaj Computer Services	B-7, Royal Plaza, Ranipur Mod, Haridwar	9359209901	Mr. Kamal Sachdeva
Uttaranchal	Kashipur	Tirpti Communications	Station Road, Main Market, Udamsingh Nagar, KASHIPUR	9837005991	Mr.Ajay Gupta
Uttaranchal	Roorkee	Geetanjali Telecom	Shop No.6, Shyam Market, BSM Tiraha, NehruNagar, Dehradun Road, Roorkee.	01332-326510	Mr. Manish Kumar
West Bengal	Assansol	Sky Computer & Telecom	Islam Market, Nuruddin Road, Assansol-713301	2207719	Syed Arshad Ali
West Bengal	Basirhat	Telelink	Bashirhat Old Market(Bowbazar).Bashirhat Dist,North 24pgs,Pin-743411	9332511610, 03217-325499	Mr. Sukanta Debnath.
West Bengal	Behrampur	CHAITANNYA ENTERPRISE	152, B B Sen Road, Sadar bazar, PO Behrampur, Distt Murshidabad,pin-742101	9333310161	SUBHAS CHANDRA BASAK
West Bengal	Bolpur	CYBER WORLD	59, SUPER MARKET, SANTINIKETAN ROAD, BOLPUR - 731204	9333739783	Mr.KISHOR KUMAR MUKHERJEE
West Bengal	Bongoan	MOLINA TRADERS	Jessore Road, Bongoan, Dist- North 24 th Pargana, PIN-743235	9332410022	Mr. Subir Dutta
West Bengal	Burdwan	San Infosys	27/1 G.T Road , East End, Burdwan -713103.	3290265	Sanjit Debnath
West Bengal	Durgapur	Digitech Service	Ashok Bhavan J.K.Pal Lane.Benachity, Durgapur -713213	3293600	Mr.Pintu Chatterjee

Person
Singh
ggarwal
Jilani
AL
(ADAV
lalhotra
Maurya
t
han
mar
Gupta
al
a
Gupta
ish
had Ali
nta
TA
JR
EE
r Dutta
bnath
e

State	City	ASC Name	ASC Address	Phone No.	Contact Person
West Bengal	Habra	JOYRAM INFOTECH	51,Jessore Road,Habra Bazar, Das Market, Dist- 24th Pargana(North), PIN-743263	237608	Mr. Malay Das
West Bengal	Haldia	DIGITRONIX	Holding no -25 ,PO Khanjanchak, PS Durgachak, Haldia, Dist- East Medinapur-721602	9332987527	Suman Jana
West Bengal	Katwa	Devarshi Mobile Communication	Bhutnath Tala, Besides Ram Bhavan, Post - Katwa, Burdwan - 713130	03453-255197	Devananda Dutta
West Bengal	Kharagpur	S. J .Communication	Inda Main Road, Khudiram Ram Market, Kharagpur.Shop No-53. Pin -721305	9333745553	Mr.Suman Jana
West Bengal	Kolkata	Benma Infosol Pvt Ltd.	P-168/1 CIT Road, Scheme VIIM, KOLKATA 700 067	033-32943176-7	Arun Surana
West Bengal	Kolkata	Friends Communication	32(8) Barasat Road,N/L 15 no railgate,PO-nonachandanpukur, PS- Titagarh, Barrackpore, Dist- North 24PGS, PIN-743102	033-25921263	Arup Sarkar & Tarasankar Mukherjee
West Bengal	Kolkata	Jaksom Engineering Pvt Ltd	Block-A, Shop-1, Ambika Vihar,1/1 Harduttrai Chamarua Road,Howrah-711001	033-32950383	P.Mukherjee
West Bengal	Kolkata	JP Computers	5B Ekdalia Place, Kolkata - 700019	033-24401923	Somim Kabir
West Bengal	Kolkata	Skylink	8/1A, Little Russel Street, Calcutta-700071	033-32903814	H R Molla
West Bengal	Kolkata	SOURAV TELECOM	195 BLOCK-J NEW ALIPUR, N/L New Alipur State Bank, KOLKATA-700053.	033-32511256	Amit Ghosh
West Bengal	Kolkata	Sun Mobile Service	15 B.T. Road, N/L Peikpara Bus Stop, Kolkata -700002	033-32505444	VIVEK KUMAR GUPTA
West Bengal	Kolkata	Sagnik	10A HO CHI MINH SARANI , KOLKATA-71	9830880150	RATHIN PAL CHOWDHURY
West Bengal	Krishnagar	ADDYA ELECTRONICS	13 MOHITOSH BISWAS STREET, P.O.KRISHNANAGAR, DIST: NADIA, PIN: 741101.	03472253031	MR ARIJIT SEN
West Bengal	Malda	Classic Services	3 No Govt Colony, Near B.B, Medecine , Malda, Pin-732101	9332293622	Mr. S.P Ganguly
West Bengal	Ranaghat	PRAYASH	30 SWAMI VIVAKNANDA SARANI, RANAGHAT, DIST-NADIA	09333515949	Mr. Amar Nath Malick
West Bengal	Serampore	Sri Guru Mobile Service	87 B/15 G.T.Road (West), Hooghly Pin-712203	033-32528581	Shyamal Kumar Das
West Bengal	Siliguri	CARE	A.T Mukherjee Road, Subhash Pally (PRANTI), Near SILIGURI COLLEGE, PO- Siliguri, Dist - Derjeeling.	9332211009	Mr.Snjoy Dutta
West Bengal	Tamluk	ZEROBIT	Vill- Parbatipur, P.O.-Tamluk, Dist- Purba Midnapur,PIN-721636	9434110802	Mr. Chanakya Sengupta

 **LG | CUSTOMER SERVICE**

*From: BSNL / MTNL



**From Mobile:
Add local STD Code

1800-180-9999*

39-01-0909**

[illegible]

U.P.